

# Junos® OS

---

Common Criteria Evaluated Configuration  
Guide for EX4400-24MP, EX4400-24P,  
EX4400-24T, EX4400-24X, EX4400-48F,  
EX4400-48MP, EX4400-48P, and  
EX4400-48T Devices

Published  
2026-03-27

RELEASE  
24.2R2

Juniper Networks, Inc.  
1133 Innovation Way  
Sunnyvale, California 94089  
USA  
408-745-2000  
[www.juniper.net](http://www.juniper.net)

Juniper Networks, the Juniper Networks logo, Juniper, and Junos are registered trademarks of Juniper Networks, Inc. in the United States and other countries. All other trademarks, service marks, registered marks, or registered service marks are the property of their respective owners.

Juniper Networks assumes no responsibility for any inaccuracies in this document. Juniper Networks reserves the right to change, modify, transfer, or otherwise revise this publication without notice.

*Junos® OS Common Criteria Evaluated Configuration Guide for EX4400-24MP, EX4400-24P, EX4400-24T, EX4400-24X, EX4400-48F, EX4400-48MP, EX4400-48P, and EX4400-48T Devices*

24.2R2

Copyright © 2026 Juniper Networks, Inc. All rights reserved.

The information in this document is current as of the date on the title page.

## YEAR 2000 NOTICE

Juniper Networks hardware and software products are Year 2000 compliant. Junos OS has no known time-related limitations through the year 2038. However, the NTP application is known to have some difficulty in the year 2036.

## END USER LICENSE AGREEMENT

The Juniper Networks product that is the subject of this technical documentation consists of (or is intended for use with) Juniper Networks software. Use of such software is subject to the terms and conditions of the End User License Agreement ("EULA") posted at <https://support.juniper.net/support/eula/>. By downloading, installing or using such software, you agree to the terms and conditions of that EULA.

# Table of Contents

About This Guide | vi

1

## Overview

Understanding the Common Criteria Evaluated Configuration | 2

Understanding Junos OS in FIPS Mode | 3

Understanding Common Criteria and FIPS Terminology and Supported Cryptographic Algorithms | 5

Identifying Secure Product Delivery | 8

Understanding Management Interfaces | 10

2

## Configuring Roles and Authentication Methods

Understanding Roles and Services for Junos OS in Common Criteria and FIPS | 12

Understanding the Operational Environment for Junos OS in FIPS Mode | 14

Understanding Password Specifications and Guidelines for Junos OS in FIPS Mode | 17

Downloading Software Packages from Juniper Networks | 19

Install Junos OS Software Package | 19

Understanding Zeroization to Clear System Data for FIPS Mode | 22

Zeroizing the System | 23

Enabling FIPS Mode | 24

Configuring Security Administrator and FIPS User Identification and Access | 31

Configuring Security Administrator Login Access | 31

Configuring FIPS User Login Access | 33

3

## Configuring Administrative Credentials and Privileges

Understanding the Associated Password Rules for an Authorized Administrator | 36

Authentication Methods in FIPS Mode of Operation | 38

**Configuring a Network Device collaborative Protection Profile for an Authorized Administrator | 39**

**Customize Time | 41**

**Configuring Inactivity Timeout Period Configuration, and Local and Remote Idle Session Termination | 41**

Configure Session Termination | 42

Sample Output for Local Administrative Session Termination | 43

Sample Output for Remote Administrative Session Termination | 43

Sample Output for User Initiated Termination | 44

4

## **Configuring SSH and Console Connection**

**Configuring a System Login Message and Announcement | 46**

**Configuring SSH on the Evaluated Configuration | 47**

**Limiting the Number of User Login Attempts for SSH Sessions | 49**

5

## **Configuring the Remote Syslog Server**

**Syslog Server Configuration on a Linux System | 53**

Configuring Event Logging to a Remote Server when Initiating the Connection from the Remote Server | 53

6

## **Configuring Audit Log Options**

**Configuring Audit Log Options in the Evaluated Configuration | 61**

Configuring Audit Log Options | 61

**Sample Code Audits of Configuration Changes | 62**

7

## **Configuring Event Logging**

**Event Logging Overview | 97**

**Configuring Event Logging to a Local File | 98**

**Interpreting Event Messages | 98**

**Logging Changes to Secret Data | 100**

**Login and Logout Events Using SSH | 100**

**Logging of Audit Startup | 101**

8

## **Configure MACsec**

**Overview of Media Access Control Security (MACsec) in FIPS mode | 103**

**Configure MACsec | 105**

Customizing Time | 105

Configuring MACsec on a Device Running Junos OS | 106

Configuring Static MACsec with Layer 3 Traffic | 107

Configuring MACsec with keychain using Layer 3 Traffic | 111

Configuring Static MACsec for Layer 2 Traffic | 117

Configuring MACsec with keychain for Layer 2 Traffic | 122

Disable and Restart MACsec Sessions | 129

9

## **Performing Self-Tests on a Device**

**Understanding FIPS Self-Tests | 132**

10

## **Operational Commands**

**request system zeroize | 137**

# About This Guide

Use this guide to configure and evaluate EX4400-24MP, EX4400-24P, EX4400-24T, EX4400-24X, EX4400-48F, EX4400-48MP, EX4400-48P, and EX4400-48T devices for Common Criteria (CC) compliance. Common Criteria for information technology is an international agreement signed by several countries that permit the evaluation of security products against a common set of standards.

## RELATED DOCUMENTATION

| [Common Criteria and FIPS Certifications](#)

# 1

CHAPTER

## Overview

---

### IN THIS CHAPTER

- Understanding the Common Criteria Evaluated Configuration | 2
  - Understanding Junos OS in FIPS Mode | 3
  - Understanding Common Criteria and FIPS Terminology and Supported Cryptographic Algorithms | 5
  - Identifying Secure Product Delivery | 8
  - Understanding Management Interfaces | 10
-

# Understanding the Common Criteria Evaluated Configuration

## IN THIS SECTION

- [Understanding Common Criteria | 2](#)
- [Supported Platforms | 2](#)

This document describes the steps required to duplicate the configuration of the device running Junos OS when the device is evaluated. This is referred to as the evaluated configuration. The following list describes the standards to which the device has been evaluated:

- NDcPP v3.0e— [https://www.commoncriteriaportal.org/files/ppfiles/NDcPP\\_v3\\_0e.pdf](https://www.commoncriteriaportal.org/files/ppfiles/NDcPP_v3_0e.pdf)

The Archived Protection Profiles documents are available at <https://www.niap-ccevs.org/Profile/PP.cfm?archived=1>.

## Understanding Common Criteria

Common Criteria for information technology is an international agreement signed by several countries that permits the evaluation of security products against a common set of standards. In the Common Criteria Recognition Arrangement (CCRA) at <https://www.commoncriteriaportal.org/ccra/>, the participants agree to mutually recognize evaluations of products performed in other countries. All evaluations are performed using a common methodology for information technology security evaluation.

For more information on Common Criteria, see <https://www.commoncriteriaportal.org/>.

Target of Evaluation (TOE) is a device or a system subjected to evaluation based on the Collaborative Protection Profile (cPP).

## Supported Platforms

For the features described in this document, the following platforms are supported:

- EX4400 Series devices (<https://www.juniper.net/us/en/products/switches/ex-series.html>).

## RELATED DOCUMENTATION

Identifying Secure Product Delivery | 8

# Understanding Junos OS in FIPS Mode

## IN THIS SECTION

- [About the Cryptographic Boundary on Your Device | 0](#)
- [How FIPS Mode Differs from Non-FIPS Mode | 4](#)
- [Validated Version of Junos OS in FIPS Mode | 4](#)

Federal Information Processing Standards (FIPS) 140-3 defines security levels for hardware and software that perform cryptographic functions.

Operating your device in a FIPS 140-3 Level 1 environment requires enabling and configuring FIPS mode on the device from the Junos OS CLI.

The *Security Administrator* enables FIPS mode in Junos OS and sets up keys and passwords for the system and other *FIPS users* who can view the configuration. Both Security Administrator and user can perform normal configuration tasks on the device (such as modify interface types) as individual user configuration allows.

## About the Cryptographic Boundary on Your Device

FIPS 140-3 compliance requires a defined *cryptographic boundary* around each *cryptographic module* on a device. Junos OS in FIPS mode prevents the cryptographic module from executing any software that is not part of the FIPS-certified distribution, and allows only FIPS-approved cryptographic algorithms to be used. No critical security parameters (CSPs), such as passwords and keys, can cross the cryptographic boundary of the module in unencrypted format.



**CAUTION:** Virtual Chassis features are not supported in FIPS mode. Do not configure a Virtual Chassis in FIPS mode.

## How FIPS Mode Differs from Non-FIPS Mode

Unlike Junos OS in non-FIPS mode, Junos OS in FIPS mode is a *non-modifiable operational environment*. In addition, Junos OS in FIPS mode differs in the following ways from Junos OS in non-FIPS mode:

- Self-tests of all cryptographic algorithms are performed at startup.
- Self-tests of random number and key generation are performed continuously.
- Weak cryptographic algorithms such as Data Encryption Standard (DES) and Message Digest 5 (MD5) are disabled.
- Weak or unencrypted management connections must not be configured. However, TOE allows local and un-encrypted console access across all modes of operation.
- Passwords must be encrypted with strong one-way algorithms that do not permit decryption.
- Junos-FIPS administrator passwords must be at least 10 characters long.
- Cryptographic keys must be encrypted before transmission.

## Validated Version of Junos OS in FIPS Mode

To determine whether a Junos OS release is NIST-validated, see the compliance page on the Juniper Networks Web site (<https://apps.juniper.net/compliance/>).

## RELATED DOCUMENTATION

| [Identifying Secure Product Delivery](#) | 8

# Understanding Common Criteria and FIPS Terminology and Supported Cryptographic Algorithms

## IN THIS SECTION

- Terminology | 5
- Supported Cryptographic Algorithms | 0

Use the definitions of Common Criteria and FIPS terms, and supported algorithms to help you understand Junos OS.

## Terminology

|                                          |                                                                                                                                                                                                                                                                                                                                                                                                                 |
|------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>Common Criteria</b>                   | Common Criteria for information technology is an international agreement signed by several countries that permits the evaluation of security products against a common set of standards.                                                                                                                                                                                                                        |
| <b>Security Administrator</b>            | For Common Criteria, user accounts in the TOE have the following attributes: user identity (user name), authentication data (password), and role (privilege). The Security Administrator is associated with the defined login class “security-admin”, which has the necessary permission set to permit the administrator to perform all tasks necessary to manage the Junos OS.                                 |
| <b>NDcPPv3.0e</b>                        | Collaborative Protection Profile for Network Devices, Version 3.0e.                                                                                                                                                                                                                                                                                                                                             |
| <b>Critical security parameter (CSP)</b> | Security-related information—for example, secret and private cryptographic keys and authentication data such as passwords and personal identification numbers (PINs)—whose disclosure or modification can compromise the security of a cryptographic module or the information it protects. For details, see <a href="#">"Understanding the Operational Environment for Junos OS in FIPS Mode" on page 14</a> . |
| <b>Cryptographic module</b>              | The set of hardware, software, and firmware that implements approved security functions (including cryptographic algorithms and key generation) and is contained within the cryptographic boundary. For fixed-configuration devices, the cryptographic                                                                                                                                                          |

module is the device case. For modular devices, the cryptographic module is the Routing Engine.

|                              |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |
|------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>FIPS</b>                  | Federal Information Processing Standards. FIPS 140-3 specifies requirements for security and cryptographic modules. Junos OS in FIPS mode complies with FIPS 140-3 Level 1.                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
| <b>FIPS maintenance role</b> | <p>The role the Security Administrator assumes to perform physical maintenance or logical maintenance services such as hardware or software diagnostics. For FIPS 140-3 compliance, the Security Administrator zeroizes the Routing Engine on entry to and exit from the FIPS maintenance role to erase all plain-text secret and private keys and unprotected CSPs.</p> <div data-bbox="431 684 1432 819">  <b>NOTE:</b> The FIPS maintenance role is not supported on Junos OS in FIPS mode. </div>                                                            |
| <b>Hashing</b>               | A message authentication method that applies a cryptographic technique iteratively to a message of arbitrary length and produces a hash <i>message digest</i> or <i>signature</i> of fixed length that is appended to the message when sent.                                                                                                                                                                                                                                                                                                                                                                                                      |
| <b>KATs</b>                  | Known answer tests. System self-tests that validate the output of cryptographic algorithms approved for FIPS and test the integrity of some Junos OS modules. For details, see <a href="#">"Understanding FIPS Self-Tests" on page 132</a> .                                                                                                                                                                                                                                                                                                                                                                                                      |
| <b>SA</b>                    | Security association (SA). A connection between hosts that allows them to communicate securely by defining, for example, how they exchange private keys. As Security Administrator, you must manually configure an internal SA on devices running Junos OS in FIPS mode. All values, including the keys, must be statically specified in the configuration. On the devices with more than one Routing Engine, the configuration must match on both ends of the connection between the Routing Engines. For communication to take place, each Routing Engine must have the same configured options, which need no negotiation and do not expire. . |
| <b>SSH</b>                   | A protocol that uses strong authentication and encryption for remote access across a nonsecure network. SSH provides remote login, remote program execution, file copy, and other functions. It is intended as a secure replacement for <b>rlogin</b> , <b>rsh</b> , and <b>rcp</b> in a UNIX environment. To secure the information sent over administrative connections, use SSHv2 for CLI configuration. In Junos OS, SSHv2 is enabled by default, and SSHv1, which is not considered secure, is disabled.                                                                                                                                     |
| <b>Zeroization</b>           | Erasure of all CSPs and other user-created data on a device before its operation as a FIPS cryptographic module—or in preparation for repurposing the device for non-FIPS                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |

operation. The Security Administrator can zeroize the system with a CLI operational command. For details, see ["Understanding Zeroization to Clear System Data for FIPS Mode" on page 22.](#)

## Supported Cryptographic Algorithms

[Table 1 on page 7](#) summarizes the high level protocol algorithm support.

**Table 1: Protocols Allowed in FIPS Mode**

| Protocol | Key Exchange                                                                                                                                          | Authentication                                                                                                                                                       | Cipher                                                                                                                       | Integrity                                                                                                |
|----------|-------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------|
| SSHv2    | <ul style="list-style-type: none"> <li>dh-group14-sha1</li> <li>ECDH-sha2-nistp256</li> <li>ECDH-sha2-nistp384</li> <li>ECDH-sha2-nistp521</li> </ul> | <ul style="list-style-type: none"> <li>ECDSA P-256</li> <li>ECDSA P-384</li> <li>ECDSA P-521</li> <li>SSH-RSA</li> <li>RSA-SHA2-256</li> <li>RSA-SHA2-512</li> </ul> | <ul style="list-style-type: none"> <li>AES CTR 128</li> <li>AES CTR 256</li> <li>AES CBC 128</li> <li>AES CBC 256</li> </ul> | <ul style="list-style-type: none"> <li>HMAC-SHA-1</li> <li>HMAC-SHA-256</li> <li>HMAC-SHA-512</li> </ul> |

The following cryptographic algorithms are supported in FIPS mode. Symmetric methods use the same key for encryption and decryption, while asymmetric methods use different keys for encryption and decryption.

**AES** The Advanced Encryption Standard (AES), defined in FIPS PUB 197. The AES algorithm uses keys of 128 or 256 bits to encrypt and decrypt data in blocks of 128 bits.

**Diffie-Hellman** A method of key exchange across a nonsecure environment (such as the Internet). The Diffie-Hellman algorithm negotiates a session key without sending the key itself across the network by allowing each party to pick a partial key independently and send part of that key to the other. Each side then calculates a common key value. This is a symmetrical method—keys are typically used only for a short time, discarded, and regenerated.

**ECDH** Elliptic Curve Diffie-Hellman. A variant of the Diffie-Hellman key exchange algorithm that uses cryptography based on the algebraic structure of elliptic curves over finite fields. ECDH allows two parties, each having an elliptic curve public-private key pair, to establish a shared secret over an insecure channel. The shared secret can be used either as a key or

to derive another key for encrypting subsequent communications using a symmetric key cipher.

|                                      |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
|--------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>ECDSA</b>                         | Elliptic Curve Digital Signature Algorithm. A variant of the Digital Signature Algorithm (DSA) that uses cryptography based on the algebraic structure of elliptic curves over finite fields. The bit size of the elliptic curve determines the difficulty of decrypting the key. The public key believed to be needed for ECDSA is about twice the size of the security strength, in bits. ECDSA uses the P-256, P-384, and P-521 curves that can be configured under OpenSSH. |
| <b>HMAC</b>                          | Defined as “Keyed-Hashing for Message Authentication” in RFC 2104, HMAC combines hashing algorithms with cryptographic keys for message authentication.                                                                                                                                                                                                                                                                                                                         |
| <b>SHA-256, SHA-384, and SHA-512</b> | Secure hash algorithms (SHA) belonging to the SHA-2 standard defined in FIPS PUB 180-2. Developed by NIST, SHA-256 produces a 256-bit hash digest, SHA-384 produces a 384-bit hash digest, and SHA-512 produces a 512-bit hash digest.                                                                                                                                                                                                                                          |
| <b>AES-CMAC</b>                      | AES-CMAC provides stronger assurance of data integrity than a checksum or an error-detecting code. The verification of a checksum or an error-detecting code detects only accidental modifications of the data, while CMAC is designed to detect intentional, unauthorized modifications of the data, as well as accidental modifications.                                                                                                                                      |

## RELATED DOCUMENTATION

[Understanding FIPS Self-Tests | 132](#)

[Understanding Zeroization to Clear System Data for FIPS Mode | 22](#)

# Identifying Secure Product Delivery

There are several mechanisms provided in the delivery process to ensure that a customer receives a product that has not been tampered with. The customer should perform the following checks upon receipt of a device to verify the integrity of the platform.

- **Shipping label**—Ensure that the shipping label correctly identifies the correct customer name and address as well as the device.
- **Outside packaging**—Inspect the outside shipping box and tape. Ensure that the shipping tape has not been cut or otherwise compromised. Ensure that the box has not been cut or damaged to allow access to the device.

- Inside packaging—Inspect the plastic bag and seal. Ensure that the bag is not cut or removed. Ensure that the seal remains intact.

If the customer identifies a problem during the inspection, he or she should immediately contact the supplier. Provide the order number, tracking number, and a description of the identified problem to the supplier.

Additionally, there are several checks that can be performed to ensure that the customer has received a box sent by Juniper Networks and not a different company masquerading as Juniper Networks. The customer should perform the following checks upon receipt of a device to verify the authenticity of the device:

- Verify that the device was ordered using a purchase order. Juniper Networks devices are never shipped without a purchase order.
- When a device is shipped, a shipment notification is sent to the e-mail address provided by the customer when the order is taken. Verify that this e-mail notification was received. Verify that the e-mail contains the following information:
  - Purchase order number
  - Juniper Networks order number used to track the shipment
  - Carrier tracking number used to track the shipment
  - List of items shipped including serial numbers
  - Address and contacts of both the supplier and the customer
- Verify that the shipment was initiated by Juniper Networks. To verify that a shipment was initiated by Juniper Networks, you should perform the following tasks:
  - Compare the carrier tracking number of the Juniper Networks order number listed in the Juniper Networks shipping notification with the tracking number on the package received.
  - Log on to the Juniper Networks online customer support portal at <https://support.juniper.net/support/> to view the order status. Compare the carrier tracking number or the Juniper Networks order number listed in the Juniper Networks shipment notification with the tracking number on the package received.

## RELATED DOCUMENTATION

# Understanding Management Interfaces

The following management interfaces can be used in the evaluated configuration:

- **Local Management Interfaces**—The RJ-45 console port on the rear panel of a device is configured as RS-232 data terminal equipment (DTE). You can use the command-line interface (CLI) over this port to configure the device from a terminal.
- **Remote Management Protocols**—The device can be remotely managed over any Ethernet interface. SSHv2 is the only permitted remote management protocol that can be used in the evaluated configuration. The remote management protocols J-Web and Telnet are not available for use on the device.

## RELATED DOCUMENTATION

[Understanding the Common Criteria Evaluated Configuration](#) | 2

# 2

CHAPTER

## Configuring Roles and Authentication Methods

---

### IN THIS CHAPTER

- Understanding Roles and Services for Junos OS in Common Criteria and FIPS | 12
  - Understanding the Operational Environment for Junos OS in FIPS Mode | 14
  - Understanding Password Specifications and Guidelines for Junos OS in FIPS Mode | 17
  - Downloading Software Packages from Juniper Networks | 19
  - Install Junos OS Software Package | 19
  - Understanding Zeroization to Clear System Data for FIPS Mode | 22
  - Zeroizing the System | 23
  - Enabling FIPS Mode | 24
  - Configuring Security Administrator and FIPS User Identification and Access | 31
-

# Understanding Roles and Services for Junos OS in Common Criteria and FIPS

## IN THIS SECTION

- [Security Administrator Role and Responsibilities | 0](#)
- [What Is Expected of All FIPS Users | 0](#)

In FIPS mode, a role refers to the specific functions or responsibilities that users have when interacting with the cryptographic module. The primary roles in FIPS mode include:

1. Security Administrator
2. FIPS user

The Security Administrator and FIPS users perform all configuration tasks for Junos OS in FIPS mode and issue all statements and commands. Security Administrator and FIPS user configurations must meet the requirements for Junos OS in FIPS mode.

The Junos OS in non-FIPS mode provides a wide range of capabilities for users and supports identity-based authentication.

## Security Administrator Role and Responsibilities

The Security Administrator role is associated with the defined login class `security-admin`. A Security Administrator has the necessary permissions to perform all tasks to manage Junos OS. The system requires administrative users (Security Administrator) to provide unique identification and authentication data before granting any administrative access.



**BEST PRACTICE:** We recommend that the Security Administrator follows security measures such as keeping passwords secure and checking audit files.

The permissions that distinguish the Security Administrator from other FIPS users are `secret`, `security`, `maintenance`, and `control`. The Security Administrator has the login class that contains all these permissions.

The Security Administrator role is crucial for maintaining the integrity and security of the system, especially in environments that require adherence to stringent federal security standards.

The Security Administrator has the following responsibilities:

1. Administer locally and remotely.
2. Create, modify, and delete user accounts, including configuration of authentication failure parameters.
3. Re-enable a user account.
4. Configure and maintain cryptographic elements related to the establishment of secure connections to and from the evaluated product.
5. Reset user passwords with FIPS-approved algorithms.
6. Examine log and audit files for events of interest.
7. Erase user-generated files, keys, and data by zeroizing the device.

### **What Is Expected of All FIPS Users**

All FIPS users, including the Security Administrator, must observe security guidelines at all times.

All FIPS users must:

- Keep all passwords confidential.
- Store devices and documentation in a secure area.
- Deploy devices in secure areas.
- Check audit files periodically.
- Conform to all other FIPS 140-3 security rules.
- Follow these guidelines:
  - Users are trusted.
  - Users abide by all security guidelines.
  - Users do not deliberately compromise security.
  - Users behave responsibly at all times.

### **RELATED DOCUMENTATION**

---

[Zeroizing the System | 23](#)

[Configuring Security Administrator and FIPS User Identification and Access | 31](#)

# Understanding the Operational Environment for Junos OS in FIPS Mode

## IN THIS SECTION

- [Hardware Environment for Junos OS in FIPS Mode | 0](#)
- [Software Environment for Junos OS in FIPS Mode | 0](#)
- [Critical Security Parameters | 0](#)

A Juniper Networks device running the Junos operating system (Junos OS) in FIPS mode forms a special type of hardware and software operational environment that is different from the environment of a device in non-FIPS mode:

### Hardware Environment for Junos OS in FIPS Mode

Junos OS in FIPS mode establishes a cryptographic boundary in the device that no critical security parameters (CSPs) can cross using plain text. Each hardware component of the device that requires a cryptographic boundary for FIPS 140-3 compliance is a separate cryptographic module. There are two types of hardware with cryptographic boundaries in Junos OS in FIPS mode: one for each Routing Engine and one for entire chassis.

Cryptographic methods are not a substitute for physical security. The hardware must be located in a secure physical environment. Users of all types must not reveal keys or passwords, or allow written records or notes to be seen by unauthorized personnel.

### Software Environment for Junos OS in FIPS Mode

A Juniper Networks device running Junos OS in FIPS mode forms a special type of non-modifiable operational environment. To achieve this environment on the device, the system prevents the execution of any binary file that was not part of the certified Junos OS distribution. When a device is in FIPS mode, it can run only Junos OS.

The Junos OS in FIPS mode software environment is established after the Security Administrator successfully enables FIPS mode on a device. The Junos OS image that includes FIPS mode is available on the Juniper Networks website and can be installed on a functioning device.

For FIPS 140-3 compliance, we recommend deleting all user-created files and data from (*zeroizing*) the system immediately after enabling FIPS mode.

Enabling FIPS mode disables many of the usual Junos OS protocols and services. In particular, you cannot configure the following services in Junos OS in FIPS mode:

- finger
- ftp
- rlogin
- telnet
- tftp
- xnm-clear-text

Attempts to configure these services, or load configurations with these services configured, result in a configuration syntax error.

You can use only SSH as a remote access service.

All passwords established for users after upgrading to Junos OS in FIPS mode must conform to Junos OS in FIPS mode specifications. Passwords must be between 10 and 20 characters in length and require the use of at least three of the five defined character sets (uppercase and lowercase letters, digits, punctuation marks, and keyboard characters, such as % and &, not included in the other four categories). Attempts to configure passwords that do not conform to these rules result in an error. All passwords and keys used to authenticate peers must be at least 10 characters in length, and in some cases the length must match the digest size.



**NOTE:** Do not attach the device to a network until you, the Security Administrator, complete the configuration from the local console connection.

For strict compliance, do not examine core and crash dump information on the local console in Junos OS in FIPS mode because some CSPs might be shown in plain text.

## Critical Security Parameters

Critical security parameters (CSPs) are security-related information such as cryptographic keys and passwords that can compromise the security of the cryptographic module or the security of the information protected by the module if they are disclosed or modified.

*Zeroization* of the system erases all traces of CSPs in preparation for operating the device or Routing Engine as a cryptographic module.

Table 2 on page 16 lists CSPs on the device running Junos OS.

**Table 2: Critical Security Parameters**

| CSP                                       | Description                                                                                                                                                                                                                                                         | Zeroization method                              | Use                                                                          |
|-------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------|------------------------------------------------------------------------------|
| SSH-2 private host key                    | ECDSA / RSA key used to identify the host, generated the first time SSH is configured.                                                                                                                                                                              | Zeroize command.                                | Used to identify the host.                                                   |
| SSH-2 session key                         | Session key used with SSHv2 and as a Diffie-Hellman private key.<br><br>Encryption: AES-128, AES-256.<br><br>MACs: HMAC-SHA-1, HMAC-SHA-2-256, HMAC-SHA2-512.<br><br>Key exchange: dh-group14-sha1, ECDH-sha2-nistp256, ECDH-sha2-nistp384, and ECDH-sha2-nistp521. | Power cycle and terminate session.              | Symmetric key used to encrypt data between host and client.                  |
| User authentication key                   | Hash of the user's password: SHA-256, SHA-512.                                                                                                                                                                                                                      | Zeroize command.                                | Used to authenticate a user to the cryptographic module.                     |
| Security Administrator authentication key | Hash of the Security Administrator's password: SHA-256, SHA-512.                                                                                                                                                                                                    | Zeroize command.                                | Used to authenticate the Security Administrator to the cryptographic module. |
| HMAC DRBG seed                            | Seed for deterministic random bit generator (DRBG).                                                                                                                                                                                                                 | Seed is not stored by the cryptographic module. | Used for seeding DRBG.                                                       |
| HMAC DRBG V value                         | The value (V) of output block length (outlen) in bits, which is updated each time another outlen bits of output are produced.                                                                                                                                       | Power cycle.                                    | A critical value of the internal state of DRBG.                              |

**Table 2: Critical Security Parameters (Continued)**

| CSP                 | Description                                                                                                                            | Zeroization method | Use                                             |
|---------------------|----------------------------------------------------------------------------------------------------------------------------------------|--------------------|-------------------------------------------------|
| HMAC DRBG key value | The current value of the outlen-bit key, which is updated at least once each time that the DRBG mechanism generates pseudorandom bits. | Power cycle.       | A critical value of the internal state of DRBG. |
| NDRNG entropy       | Used as entropy input string to the HMAC DRBG.                                                                                         | Power cycle.       | A critical value of the internal state of DRBG. |

In Junos OS in FIPS mode, all CSPs must enter and leave the cryptographic module in encrypted form. Any CSP encrypted with a non-approved algorithm is considered plain text by FIPS.

Local passwords are hashed with the secure hash algorithm SHA-256, or SHA-512. Password recovery is not possible in Junos OS in FIPS mode. Junos OS in FIPS mode cannot boot into single-user mode without the correct root password.

## RELATED DOCUMENTATION

[Understanding Password Specifications and Guidelines for Junos OS in FIPS Mode | 17](#)

[Understanding Zeroization to Clear System Data for FIPS Mode | 22](#)

# Understanding Password Specifications and Guidelines for Junos OS in FIPS Mode

Ensure that the device is in FIPS mode before you configure the Security Administrator or any users. All passwords established for users by the Security Administrator must conform to the following Junos OS in FIPS mode requirements. Attempts to configure passwords that do not conform to the following specifications result in an error.

- Length. The passwords must contain at least 10 characters.
- Character set requirements. Passwords must contain at least three of the following five defined character sets:

- Uppercase letters
- Lowercase letters
- Digits
- Punctuation marks
- Keyboard characters not included in the other four sets—such as the percent sign (%) and the ampersand (&)
- Authentication requirements. All passwords and keys used to authenticate peers must contain at least 10 characters, and in some cases the number of characters must match the digest size.
- Password encryption: To change the default encryption method (SHA512) include the `format` statement at the `[edit system login password]` hierarchy level.

Guidelines for strong passwords. Strong, reusable passwords can be based on letters from a favorite phrase or word and then concatenated with other unrelated words, along with added digits and punctuation. In general, a strong password is:

- Easy to remember so that users are not tempted to write it down.
- Made up of mixed alphanumeric characters and punctuation. For FIPS compliance include at least one change of case, one or more digits, and one or more punctuation marks.
- Changed periodically.
- Not divulged to anyone.

Characteristics of weak passwords. Do not use the following weak passwords:

- Words that might be found in or exist as a permuted form in a system files such as `/etc/passwd`.
- The hostname of the system (always a first guess).
- Any word or phrase that appears in a dictionary or other well-known source, including dictionaries and thesauruses in languages other than English; works by classical or popular writers; or common words and phrases from sports, sayings, movies or television shows.
- Permutations on any of the above—for example, a dictionary word with letters replaced with digits (**root**) or with digits added to the end.
- Any machine-generated password. Algorithms reduce the search space of password-guessing programs and so must not be used.

## RELATED DOCUMENTATION

Understanding the Operational Environment for Junos OS in FIPS Mode | 14

# Downloading Software Packages from Juniper Networks

You can download the Junos OS software package from the Juniper Networks website.

Before you begin to download the software, ensure that you have a Juniper Networks Web account and a valid support contract. To obtain an account, complete the registration form at the Juniper Networks website: <https://userregistration.juniper.net/>.

To download software packages from Juniper Networks:

1. Using a Web browser, follow the links to the download URL on the Juniper Networks webpage.  
<https://support.juniper.net/support/downloads/>
2. Log in to the Juniper Networks authentication system using the username (generally your e-mail address) and password supplied by Juniper Networks representatives.
3. Download the software. See [Downloading Software](#).

## RELATED DOCUMENTATION

Install Junos OS Software Package | 19

# Install Junos OS Software Package

You can use this procedure to upgrade Junos OS on the device with a single Routing Engine.



**NOTE:** Junos OS packages contain manifests that include the hash values and digital signature of the packages. During software installation, Junos OS verifies these hash values and digital signature of the software packages. The installation proceeds only if the verification is successful.

To install software upgrades on your device with a single Routing Engine:

1. Download the software package as described in "[Downloading Software Packages from Juniper Networks](#)" on page 19.
2. If you have not already done so, connect to the console port on the device from your management device, and log in to the Junos OS CLI.
3. (Optional) Back up the current software configuration to a second storage option. See the [Junos OS Installation and Upgrade Guide](#) for instructions on performing this task.
4. (Optional) Copy the software package to the device. We recommend that you use FTP to copy the file to the `/var/tmp/` directory.

This step is optional because Junos OS can also be upgraded when the software image is stored at a remote location. These instructions describe the software upgrade process for both scenarios.

5. Install the new package on the device:

```
user@host> request system software add package
```

Replace *package* with one of the following paths:

- For a software package in a local directory on the device, use `/var/tmp/package.tgz`.
- For a software package on a remote server, use one of the following paths, replacing *package* with the software package name.
  - `ftp://hostname/pathname/package.tgz`
  - `http://hostname/pathname/package.tgz`



**NOTE:** If you need to terminate the installation, do not reboot your device; instead, finish the installation and then issue the `request system software delete package.tgz` command. This is your last chance to stop the installation.

6. Reboot the device to load the installation and start the new software:

```
user@host> request system reboot
```

7. After the reboot has completed, log in and use the `show version` command to verify that the new version of the software is successfully installed.

```
user@host> show version
Hostname: host
Model: ex4400-24mp
Junos: 24.2R2.18
xJUNOS OS Kernel 64-bit [20241123.ec94286_builder_bsd15_242]
```

```

JUNOS early ex config [20250221.075806_builder_junos_242_r2]
JUNOS ex runtime [20250221.075806_builder_junos_242_r2]
JUNOS ex platform support [20250221.075806_builder_junos_242_r2]
JUNOS OS libs compat32 [20241123.ec94286_builder_bsd15_242]
JUNOS modules [20250221.075806_builder_junos_242_r2]
JUNOS OS libs [20241123.ec94286_builder_bsd15_242]
JUNOS ex modules [20250221.075806_builder_junos_242_r2]
JUNOS OS 32-bit compatibility [20241123.ec94286_builder_bsd15_242]
JUNOS OS runtime [20241123.ec94286_builder_bsd15_242]
JUNOS OS EFI boot files [20241123.ec94286_builder_bsd15_242]
JUNOS OS time zone information [20241123.ec94286_builder_bsd15_242]
JUNOS network stack and utilities [20250221.075806_builder_junos_242_r2]
JUNOS libs [20250221.075806_builder_junos_242_r2]
JUNOS py extensions [20250221.075806_builder_junos_242_r2]
JUNOS py base [20250221.075806_builder_junos_242_r2]
JUNOS OS package [20241014.220147_builder_main]
JUNOS OS EFI runtime [20241123.ec94286_builder_bsd15_242]
JUNOS OS crypto [20241123.ec94286_builder_bsd15_242]
JUNOS OS boot files [20241123.ec94286_builder_bsd15_242]
JUNOS SDN Software Suite [20250221.075806_builder_junos_242_r2]
JUNOS jail runtime [20241123.ec94286_builder_bsd15_242]
JUNOS dcp network modules [20250221.075806_builder_junos_242_r2]
JUNOS libs compat32 [20250221.075806_builder_junos_242_r2]
JUNOS ex libs compat32 [20250221.075806_builder_junos_242_r2]
JUNOS OS network modules [20241123.ec94286_builder_bsd15_242]
JUNOS daemons [20250221.075806_builder_junos_242_r2]
JUNOS runtime [20250221.075806_builder_junos_242_r2]
JUNOS Routing aggregated [20250221.075806_builder_junos_242_r2]
JUNOS probe utility [20250221.075806_builder_junos_242_r2]
JUNOS system counters [20250221.075806_builder_junos_242_r2]
JUNOS Openconfig [24.2R2.18]
JUNOS L2 RSI Scripts [20250221.075806_builder_junos_242_r2]
JUNOS Web Management Platform Package [20250221.075806_builder_junos_242_r2]
JUNOS support scripts [20250221.075806_builder_junos_242_r2]
JUNOS python routing scripts for consistency check in RIB/FIB/PFE
[20250221.075806_builder_junos_242_r2]
JUNOS Routing mpls-oam-basic [20250221.075806_builder_junos_242_r2]
JUNOS Routing lsys [20250221.075806_builder_junos_242_r2]
JUNOS Routing 32-bit Compatible Version [20250221.075806_builder_junos_242_r2]
JUNOS lite sysmond [20250221.075806_builder_junos_242_r2]
JUNOS EX PFE LOGGING [20250221.075806_builder_junos_242_r2]
JUNOS Extension Toolkit [20250221.075806_builder_junos_242_r2]
JUNOS Phone-home [20250221.075806_builder_junos_242_r2]

```

```

JUNOS Packet Forwarding Engine Support (EX44XX) [20250221.075806_builder_junos_242_r2]
JUNOS jdocs ex [20250221.075806_builder_junos_242_r2]
JUNOS ex Common BIOS [20250221.075806_builder_junos_242_r2]
JUNOS dsa [20250221.075806_builder_junos_242_r2]
JUNOS FIPS mode utilities [20250221.075806_builder_junos_242_r2]
JUNOS na telemetry [24.2R2.18]
JUNOS ex Data Plane Crypto Support [20250221.075806_builder_junos_242_r2]

```

## Understanding Zeroization to Clear System Data for FIPS Mode

### IN THIS SECTION

- [Why Zeroize? | 23](#)
- [When to Zeroize? | 23](#)

Zeroization completely erases all configuration information on the Routing Engines, including all plain-text passwords, secrets, and private keys for SSH, local encryption, and local authentication.

The Security Administrator initiates the zeroization process by entering the **request system zeroize** operational command from the CLI after enabling FIPS mode. Use of this command is restricted to the Security Administrator.



**CAUTION:** Perform system zeroization with care. After the zeroization process is complete, no data is left on the Routing Engine. The device is returned to the factory default state, without any configured users or configuration files.

Zeroization can be time-consuming. Although all configurations are removed in a few seconds, the zeroization process goes on to overwrite all media, which can take considerable time depending on the size of the media.

## Why Zeroize?

Your device is not considered a valid FIPS cryptographic module until all critical security parameters (CSPs) have been entered—or reentered—while the device is in FIPS mode. For FIPS 140-3 compliance, the only way to exit from FIPS mode is to zeroize the TOE.

## When to Zeroize?

As Security Administrator, perform zeroization in the following situations:

- Before Enabling FIPS mode of operation: To prepare your device for operation as a FIPS cryptographic module, perform zeroization before enabling FIPS mode.
- Before repurposing to non-FIPS mode of operation: To begin repurposing your device for non-FIPS mode of operation, perform zeroization on the device.



**NOTE:** Juniper Networks does not support installing non-FIPS software in a FIPS environment, but doing so might be necessary in certain test environments. Be sure to zeroize the system first.

## RELATED DOCUMENTATION

| [Enabling FIPS Mode](#) | 24

# Zeroizing the System

Your device is not considered a valid FIPS cryptographic module until all critical security parameters (CSPs) have been entered—or reentered—while the device is in FIPS mode.

For FIPS 140-3 compliance, you must zeroize the system to remove sensitive information before disabling FIPS mode on the device.

As Security Administrator, you run the `request system zeroize` command to remove all user-created files from a device and replace the user data with zeros. This command completely erases all configuration information on the Routing Engines, including all rollback configuration files and plain-text passwords, secrets, and private keys for SSH, local encryption, and local authentication.

To zeroize your device:



**CAUTION:** Perform system zeroization with care. After the zeroization process is complete, no data is left on the Routing Engine. The device is returned to the factory default state, without any configured users or configuration files.

1. From the CLI, enter

```
root@host> request system zeroize
warning: System will be rebooted and may not boot without configuration
Erase all data, including configuration and log files?  [yes, no] (no)
```

2. To initiate the zeroization process, type **yes** at the prompt:

```
Erase all data, including configuration and log files?  [yes, no] (no) yes
warning: zeroizing localre
```

The entire operation can take considerable time depending on the size of the media, but all critical security parameters (CSPs) are removed within a few seconds. The physical environment must remain secure until the zeroization process is complete.

## RELATED DOCUMENTATION

[Enabling FIPS Mode | 24](#)

[Understanding Zeroization to Clear System Data for FIPS Mode | 22](#)

# Enabling FIPS Mode

FIPS mode is not automatically enabled when you install Junos OS on the device.

As Security Administrator, you must explicitly enable FIPS mode on the device by setting the FIPS level to 1 (one), the FIPS 140-3 level at which the devices are certified. A device on which FIPS mode is not enabled has a FIPS level of 0 (zero).



**NOTE:** To transition to FIPS mode, passwords must be encrypted with a FIPS-compliant hash algorithm. The encryption format must be SHA-256 or higher. Passwords that do

not meet this requirement, such as passwords that are hashed with MD5, must be reconfigured or removed from the configuration before FIPS mode can be enabled.

To enable FIPS mode in Junos OS on the device:

1. Enter configuration mode:

```
root@host> configure
Entering configuration mode
[edit]
root@host#
```

2. Enable FIPS mode on the device by setting the FIPS level to 1, and verify the level:

```
[edit]
root@host# set system fips level 1
```

```
[edit]
root@host#show system
fips {
  level 1;
}
```

3. After zeroize, the factory-default configuration enables the DHCP client and netconf-ssh. Disable the DHCP client and configure a firewall filter to restrict access to the netconf-ssh service.

To disable DHCP service:

```
[edit]
security-administrator@host:fips# set system processes dhcp-service disable
```

To configure firewall filter for netconf-ssh service:

```
{master:0}
[edit firewall family inet]
security-administrator@host:fips# show
filter PROTECT-NETCONF {
  term DENY-NETCONF {
    from {
```

```

        protocol tcp;
        destination-port 830;
    }
    then {
        discard;
    }
}
term ACCEPT-ALL {
    then accept;
}
}

```

4. Commit the configuration:



**NOTE:** If the device terminal displays error messages about the presence of critical security parameters (CSPs), delete those CSPs, and then commit the configuration.

```

root@host# commit
configuration check succeeds
[edit]
'system'
    reboot is required to transition to FIPS level 1
commit complete

```

5. Reboot the device:

```

[edit]
root@host# run request system reboot
Reboot the system ? [yes,no] (no) yes

```

During the reboot, the device runs Known Answer Tests (KATS). It returns a login prompt:



**NOTE:** The new hash algorithm affect only those passwords that are generated after commit.

```

@ 1556787428 mgd start
Creating initial configuration: ...
mgd: Running FIPS Self-tests

```

```

random: HMAC-DRBG with SHA2-512 chosen
sysctl_warn_reuse: can't re-use a leaf (kern.random.hmac-drbg.hash)!
mgd: Testing kernel KATS:
mgd: NIST 800-90 HMAC DRBG Known Answer Test:           Passed
mgd: HMAC-SHA1 Known Answer Test:                       Passed
mgd: HMAC-SHA2-256 Known Answer Test:                   Passed
mgd: SHA-2-384 Known Answer Test:                       Passed
mgd: SHA-2-512 Known Answer Test:                       Passed
mgd: AES128-CMAC Known Answer Test:                     Passed
mgd: AES-CBC Known Answer Test:                         Passed
mgd: Testing MACSec KATS:
mgd: AES128-CMAC Known Answer Test:                     Passed
mgd: AES256-CMAC Known Answer Test:                     Passed
mgd: AES-ECB Known Answer Test:                         Passed
mgd: AES-KEYWRAP Known Answer Test:                     Passed
mgd: KBKDF Known Answer Test:                           Passed
mgd: Testing libmd KATS:
mgd: HMAC-SHA1 Known Answer Test:                       Passed
mgd: HMAC-SHA2-256 Known Answer Test:                   Passed
mgd: SHA-2-512 Known Answer Test:                       Passed
mgd: Testing OpenSSL KATS:
mgd: FIPS ECDSA Known Answer Test:                       Passed
mgd: FIPS ECDH Known Answer Test:                       Passed
mgd: HMAC-SHA1 Known Answer Test:                       Passed
mgd: HMAC-SHA2-224 Known Answer Test:                   Passed
mgd: HMAC-SHA2-256 Known Answer Test:                   Passed
mgd: HMAC-SHA2-384 Known Answer Test:                   Passed
mgd: HMAC-SHA2-512 Known Answer Test:                   Passed
mgd: AES-CBC Known Answer Test:                         Passed
mgd: AES-GCM Known Answer Test:                         Passed
mgd: RSA-ENC Known Answer Test:                         Passed
mgd: RSA-SIGN Known Answer Test:                        Passed
mgd: KDF-IKE-V1 Known Answer Test:                      Passed
mgd: KDF-SSH-SHA256 Known Answer Test:                  Passed
mgd: KDF-TLS12-PRF Known Answer Test:                   Passed
mgd: KDF-TLS13-KDF-EXTRACT Known Answer Test:           Passed
mgd: KDF-TLS13-KDF-EXPAND Known Answer Test:             Passed
mgd: KDF-X942 Known Answer Test:                        Passed
mgd: KDF-X963 Known Answer Test:                        Passed
mgd: KAS-ECC-EPHEM-UNIFIED-NOKC Known Answer Test:      Passed
mgd: KAS-FFC-EPHEM-NOKC Known Answer Test:              Passed
mgd: Testing QuickSec 7.0 KATS:
mgd: HMAC-SHA1 Known Answer Test:                       Passed

```

```

mgd: HMAC-SHA2-224 Known Answer Test:      Passed
mgd: HMAC-SHA2-256 Known Answer Test:      Passed
mgd: HMAC-SHA2-384 Known Answer Test:      Passed
mgd: HMAC-SHA2-512 Known Answer Test:      Passed
mgd: AES-CBC Known Answer Test:            Passed
mgd: AES-GCM Known Answer Test:            Passed
mgd: SSH-RSA-ENC Known Answer Test:        Passed
mgd: SSH-RSA-SIGN Known Answer Test:       Passed
mgd: SSH-ECDSA-SIGN Known Answer Test:     Passed
mgd: KDF-IKE-V1 Known Answer Test:        Passed
mgd: KDF-IKE-V2 Known Answer Test:        Passed
mgd: Testing QuickSec KATS:
mgd: HMAC-SHA1 Known Answer Test:          Passed
mgd: HMAC-SHA2-224 Known Answer Test:      Passed
mgd: HMAC-SHA2-256 Known Answer Test:      Passed
mgd: HMAC-SHA2-384 Known Answer Test:      Passed
mgd: HMAC-SHA2-512 Known Answer Test:      Passed
mgd: AES-CBC Known Answer Test:            Passed
mgd: AES-GCM Known Answer Test:            Passed
mgd: SSH-RSA-ENC Known Answer Test:        Passed
mgd: SSH-RSA-SIGN Known Answer Test:       Passed
mgd: KDF-IKE-V1 Known Answer Test:        Passed
mgd: KDF-IKE-V2 Known Answer Test:        Passed
mgd: Testing SSH IPsec KATS:
mgd: HMAC-SHA1 Known Answer Test:          Passed
mgd: HMAC-SHA2-256 Known Answer Test:      Passed
mgd: AES-CBC Known Answer Test:            Passed
mgd: SSH-RSA-ENC Known Answer Test:        Passed
mgd: SSH-RSA-SIGN Known Answer Test:       Passed
mgd: KDF-IKE-V1 Known Answer Test:        Passed
mgd: Testing file integrity:
mgd: File integrity Known Answer Test:      Passed
mgd: Testing crypto integrity:
mgd: Crypto integrity Known Answer Test:    Passed
mgd: Expect an exec Authentication error...
mgd: /sbin/kats/run-tests: /sbin/kats/cannot-exec: Authentication error
mgd: FIPS Self-tests Passed

```

Log in to the device. The CLI displays a banner that is followed by a prompt that includes “:fips”:

```
--- JUNOS 24.2R2.18 Kernel 64-bit JNPR-15.0-20240618.78e5114_buil
root@host:fips>
```

6. Reboot the device again to restore the HMAC-DRBG as an active random adapter:

```
[edit]
root@host# run request system reboot
Reboot the system ? [yes,no] (no) yes
```

During the reboot, the device runs Known Answer Tests (KATS) as shown in the step 4. It returns a login prompt:

```
--- JUNOS 24.2R2.18 Kernel 64-bit JNPR-15.0-20240618.78e5114_buil
root@host:fips>
```

7. After the reboot has completed, log in and use the `show version local` command to verify.

```
user@host:fips> show version local
Hostname: host
Model: ex4400-24mp
Junos: 24.2R2.18
JUNOS OS Kernel 64-bit [20241123.ec94286_builder_bsd15_242]
JUNOS early ex config [20250221.075806_builder_junos_242_r2]
JUNOS ex runtime [20250221.075806_builder_junos_242_r2]
JUNOS ex platform support [20250221.075806_builder_junos_242_r2]
JUNOS OS libs compat32 [20241123.ec94286_builder_bsd15_242]
JUNOS modules [20250221.075806_builder_junos_242_r2]
JUNOS OS libs [20241123.ec94286_builder_bsd15_242]
JUNOS ex modules [20250221.075806_builder_junos_242_r2]
JUNOS OS 32-bit compatibility [20241123.ec94286_builder_bsd15_242]
JUNOS OS runtime [20241123.ec94286_builder_bsd15_242]
JUNOS OS EFI boot files [20241123.ec94286_builder_bsd15_242]
JUNOS OS time zone information [20241123.ec94286_builder_bsd15_242]
JUNOS network stack and utilities [20250221.075806_builder_junos_242_r2]
JUNOS libs [20250221.075806_builder_junos_242_r2]
JUNOS py extensions [20250221.075806_builder_junos_242_r2]
JUNOS py base [20250221.075806_builder_junos_242_r2]
JUNOS OS package [20241014.220147_builder_main]
```

```

JUNOS OS EFI runtime [20241123.ec94286_builder_bsd15_242]
JUNOS OS crypto [20241123.ec94286_builder_bsd15_242]
JUNOS OS boot files [20241123.ec94286_builder_bsd15_242]
JUNOS SDN Software Suite [20250221.075806_builder_junos_242_r2]
JUNOS jail runtime [20241123.ec94286_builder_bsd15_242]
JUNOS dcp network modules [20250221.075806_builder_junos_242_r2]
JUNOS libs compat32 [20250221.075806_builder_junos_242_r2]
JUNOS ex libs compat32 [20250221.075806_builder_junos_242_r2]
JUNOS OS network modules [20241123.ec94286_builder_bsd15_242]
JUNOS daemons [20250221.075806_builder_junos_242_r2]
JUNOS runtime [20250221.075806_builder_junos_242_r2]
JUNOS Routing aggregated [20250221.075806_builder_junos_242_r2]
JUNOS probe utility [20250221.075806_builder_junos_242_r2]
JUNOS system counters [20250221.075806_builder_junos_242_r2]
JUNOS Openconfig [24.2R2.18]
JUNOS L2 RSI Scripts [20250221.075806_builder_junos_242_r2]
JUNOS Web Management Platform Package [20250221.075806_builder_junos_242_r2]
JUNOS support scripts [20250221.075806_builder_junos_242_r2]
JUNOS python routing scripts for consistency check in RIB/FIB/PFE
[20250221.075806_builder_junos_242_r2]
JUNOS Routing mpls-oam-basic [20250221.075806_builder_junos_242_r2]
JUNOS Routing lsys [20250221.075806_builder_junos_242_r2]
JUNOS Routing 32-bit Compatible Version [20250221.075806_builder_junos_242_r2]
JUNOS lite sysmond [20250221.075806_builder_junos_242_r2]
JUNOS EX PFE LOGGING [20250221.075806_builder_junos_242_r2]
JUNOS Extension Toolkit [20250221.075806_builder_junos_242_r2]
JUNOS Phone-home [20250221.075806_builder_junos_242_r2]
JUNOS Packet Forwarding Engine Support (EX44XX) [20250221.075806_builder_junos_242_r2]
JUNOS jdocs ex [20250221.075806_builder_junos_242_r2]
JUNOS ex Common BIOS [20250221.075806_builder_junos_242_r2]
JUNOS dsa [20250221.075806_builder_junos_242_r2]
JUNOS FIPS mode utilities [20250221.075806_builder_junos_242_r2]
JUNOS na telemetry [24.2R2.18]
JUNOS ex Data Plane Crypto Support [20250221.075806_builder_junos_242_r2]

```



**NOTE:** Use “local” keyword for operational commands in FIPS mode. For example, show version local, and show system uptime local.

# Configuring Security Administrator and FIPS User Identification and Access

## IN THIS SECTION

- [Configuring Security Administrator Login Access | 31](#)
- [Configuring FIPS User Login Access | 33](#)

Security Administrator and FIPS users perform all configuration tasks for Junos OS in FIPS mode and issue all Junos OS in FIPS mode statements and commands. Security Administrator and FIPS user configurations must follow Junos OS in FIPS mode guidelines.

## Configuring Security Administrator Login Access

Junos OS in FIPS mode offers a finer granularity of user permissions than those mandated by FIPS 140-3.

For FIPS 140-3 compliance, any FIPS user with the **secret**, **security**, **maintenance**, and **control** permission bits set is a Security Administrator. In most cases the **super-user** class suffices for the Security Administrator.

To configure login access for a Security Administrator:

1. Log in to the device with the root password if you have not already done so, and enter configuration mode:

```
root@host:fips> configure
Entering configuration mode
[edit]
root@host:fips#
```

2. Name the user **crypto-officer** and assign the Security Administrator a user ID (for example, **6400**) and a class (for example, **security-admin**). When you assign the class, you assign the permissions—for example, **secret**, **security**, **maintenance**, and **control**.

```
[edit]
root@host:fips# set system login user crypto-officer uid 6400 class security-admin
```

3. Following the guidelines in ["Understanding Password Specifications and Guidelines for Junos OS in FIPS Mode" on page 17](#), assign the Security Administrator a plain-text password for login authentication. Set the password by typing a password after the prompts New password and Retype new password.

```
[edit]
root@host:fips# set system login user crypto-officer class security-admin authentication
plain-text-password
```

4. Optionally, display the configuration:

```
[edit]
root@host:fips# edit system
[edit system]
root@host:fips# show
login {
    user crypto-officer {
        uid 6400;
        authentication {
            encrypted-password "<cipher-text>"; ## SECRET-DATA
        }
        class security-admin;
    }
}
```

5. If you are finished configuring the device, commit the configuration and exit:

```
[edit]
root@host:fips# commit
commit complete
root@host:fips# exit
root@host:fips> exit
```

Otherwise, go on to ["Configuring FIPS User Login Access" on page 33](#).

## Configuring FIPS User Login Access

A **fips-user** is defined as any FIPS user that does not have the **secret**, **security**, **maintenance**, and **control** permission bits set. As the Security Administrator, you set up FIPS users.

To configure login access for a FIPS user:

1. Log in to the device with your Security Administrator password if you have not already done so, and enter configuration mode:

```
crypto-officer@host:fips> configure
Entering configuration mode
[edit]
crypto-officer@host:fips#
```

2. Give the user a username, assign the FIPS user a user ID (for example, **6401**) and a class (for example, **read-only**). When you assign the class, you assign the permissions—for example, **clear**, **configure**, **network**, **resetview**, and **view-configuration**.

```
[edit]
crypto-officer@host:fips# set system login user fips-user1 uid 6401 class read-only
```

3. Following the guidelines in "[Understanding Password Specifications and Guidelines for Junos OS in FIPS Mode](#)" on page 17, assign the FIPS a plain-text password for login authentication. Set the password by typing a password after the prompts **New password** and **Retype new password**.

```
[edit]
crypto-officer@host:fips# set system login user fips-user1 class operator authentication
plain-text-password
```

4. Optionally, display the configuration:

```
[edit]
crypto-officer@host:fips# edit system
[edit system]
crypto-officer@host:fips# show
login {
  user fips-user1 {
    uid 6401;
    authentication {
```

```
        encrypted-password "<cipher-text>"; ## SECRET-DATA
    }
    read-only;
}
}
```

5. If you are finished configuring the device, commit the configuration and exit:

```
[edit]
crypto-officer@host:fips# commit
crypto-officer@host:fips> exit
```

## RELATED DOCUMENTATION

[Understanding Roles and Services for Junos OS in Common Criteria and FIPS](#) | 12

# 3

CHAPTER

## Configuring Administrative Credentials and Privileges

---

### IN THIS CHAPTER

- Understanding the Associated Password Rules for an Authorized Administrator | **36**
  - Authentication Methods in FIPS Mode of Operation | **38**
  - Configuring a Network Device collaborative Protection Profile for an Authorized Administrator | **39**
  - Customize Time | **41**
  - Configuring Inactivity Timeout Period Configuration, and Local and Remote Idle Session Termination | **41**
-

# Understanding the Associated Password Rules for an Authorized Administrator

The authorized administrator is associated with a defined login class, and the administrator is assigned with all permissions. Data is stored locally for fixed password authentication.



**NOTE:** We recommend that you not use control characters in passwords.

Use the following guidelines and configuration options for passwords and when selecting passwords for authorized administrator accounts. Passwords should be:

- Easy to remember so that users are not tempted to write it down.
- Changed periodically.
- Private and not shared with anyone.
- Contain a minimum of 10 characters. The minimum password length is 10 characters.
- Include both alphanumeric and punctuation characters, composed of any combination of upper and lowercase letters, numbers, and special characters such as, "!", "@", "#", "\$", "%", "^", "&", "\*", "(", and ")". There should be at least a change in one case, one or more digits, and one or more punctuation marks.
- Contain character sets. Valid character sets include uppercase letters, lowercase letters, numbers, punctuation, and other special characters.

[ edit ]

```
security-administrator@host# set system login password change-type character-sets
```

- Contain the minimum number of character sets or character set changes. The minimum number of character sets required in plain-text passwords in Junos FIPS is 3.

[ edit ]

```
security-administrator@host# set system login password minimum-changes 3
```

- Contain the minimum number of characters required for a password. By default, Junos OS passwords must be at least 6 characters long. The valid range for this option is 10 to 20 characters.

```
[ edit ]
security-administrator@host:fips# set system login password minimum-length 10
```



**NOTE:** The device supports ECDSA (P-256, P-384, and P-521) and RSA (2048, 3072, and 4092 modulus bit length) key-types.

```
[ edit ]
administrator@host# set system login password format sha256
```

Weak passwords are:

- Words that might be found in or exist as a permuted form in a system file such as `/etc/passwd`.
- The hostname of the system (always a first guess).
- Any words appearing in a dictionary. This includes dictionaries other than English, and words found in works such as Shakespeare, Lewis Carroll, Roget's Thesaurus, and so on. This prohibition includes common words and phrases from sports, sayings, movies, and television shows.
- Permutations on any of the above. For example, a dictionary word with vowels replaced with digits (for example f00t) or with digits added to the end.
- Any machine-generated passwords. Algorithms reduce the search space of password-guessing programs and so should not be used.

Strong reusable passwords can be based on letters from a favorite phrase or word, and then concatenated with other, unrelated words, along with additional digits and punctuation.



**NOTE:** Passwords should be changed periodically.

## RELATED DOCUMENTATION

Identifying Secure Product Delivery | 8

# Authentication Methods in FIPS Mode of Operation

## IN THIS SECTION

- Username and Password Authentication over the Console and SSH | 0
- Username and Public Key Authentication over SSH | 0

The Juniper Networks Junos operating system (Junos OS) running in FIPS mode of operation allows a wide range of capabilities for users, and authentication is identity-based. The following types of identity-based authentication are supported in the FIPS mode of operation:

### Username and Password Authentication over the Console and SSH

In this authentication method, the user is requested to enter the username and password after logging in to the TOE. The device enforces the user to enter a minimum of 10-characters password that is chosen from the 95 human-readable ASCII characters, as per <https://www.ascii-code.com/> excluding the DEL ASCII code.



**NOTE:** The maximum password length is 20 characters.

In this method, the device enforces a timed access mechanism—for example, first two failed attempts to enter the correct password (assuming 0 time to process), no timed access is enforced. When the user enters the password for the third time, the module enforces a 5-second delay. Each failed attempt thereafter results in an additional 5-second delay above the previous failed attempt. For example, if the fourth failed attempt is a 10-second delay, then the fifth failed attempt is a 15-second delay, the sixth failed attempt is a 20-second delay, and the seventh failed attempt is a 25-second delay.

Therefore, this leads to a maximum of seven possible attempts in a 1-minute period for each getty active terminal. So, the best approach for the attacker would be to disconnect after 4 failed attempts, and wait for a new getty to be spawned. This would allow the attacker to perform roughly 9.6 attempts per minute (576 attempts per hour or 60 minutes). This would be rounded off to 9 attempts per minute, because there is no such thing as 0.6 attempts. Thus the probability of a successful random attempt is  $1/9610$ , which is less than  $1/1$  million. The probability of a success with multiple consecutive attempts in a 1-minute period is  $9/(9610)$ , which is less than  $1/100,000$ .

## Username and Public Key Authentication over SSH

With SSH public-key authentication, the user provides the username and proves ownership of the private key corresponding to the public key stored on the server. The device supports ECDSA (P-256, P-384, and P-521) and RSA (2048-bit or higher since our RSA implementation is FIPS 186-4 compliant). The probability of a success with multiple consecutive attempts in a 1-minute period is  $5.6e7/(2^{128})$ .

### RELATED DOCUMENTATION

| [Configuring SSH on the Evaluated Configuration](#) | 47

## Configuring a Network Device collaborative Protection Profile for an Authorized Administrator

An account for root is always present in a configuration and is not intended for use in normal operation. In the evaluated configuration, the root account is restricted to the initial installation and configuration of the evaluated device.

An NDcPP Version 3.0e authorized administrator must have all permissions, including the ability to change the router configuration.

To configure an authorized administrator:

1. Create a login class named **security-admin** with all permissions.

```
[edit]
root@host# set system login class security-admin permissions all
```

2. Create a user **crypto-officer** and assign **security-admin** class.

```
[edit]
root@host# set system login user crypto-officer class security-admin
```

3. Configure the hashing algorithm used for password storage as sha512.

```
root@host# set system login password format sha512
```



**NOTE:** For your security devices, the default password algorithm is sha512, and it is not necessary to configure the plain-text passwords for EX and QFX series switches.

4. Define your NDcPP Version 3.0e authorized administrator.

```
[edit]
root@host# set system login user crypto-officer authentication plain-text-password
New password:
Retype new password:
```

5. (Optional) Load an SSH key file that was previously generated using ssh-keygen. This command loads RSA (SSH version 2), or ECDSA (SSH version 2).

```
[edit]
root@host# set system login user crypto-officer authentication load-key-file url:filename
```

6. Set the log-key-changes configuration statement to log when SSH authentication keys are added or removed.

```
[edit]
root@host# set system services ssh log-key-changes
```



**NOTE:** When the log-key-changes configuration statement is enabled and committed (with the commit command in configuration mode), Junos OS logs the changes to the set of authorized SSH keys for each user (including the keys that were added or removed). Junos OS logs the differences since the last time the log-key-changes configuration statement was enabled. If the log-key-changes configuration statement was never enabled, then Junos OS logs all the authorized SSH keys.

7. Commit the changes.

```
[edit]
root@host# commit
```

## RELATED DOCUMENTATION

[Understanding the Associated Password Rules for an Authorized Administrator](#) | 36

# Customize Time

To customize time, enable NTP or set the date from the Junos OS CLI.

1. Enable NTP.

```
[edit]
security-administrator@hostname:fips# set system ntp server 10.1.1..1 key 1
security-administrator@hostname:fips# set system ntp authentication-key 1 type [sha256] value
12345678
security-administrator@hostname:fips# set system ntp trusted-key 1
security-administrator@hostname:fips# commit
```

2. If you do not use NTP, set the date and time from the CLI. Date and time format is YYYYMMDDHHMM.ss

```
security-administrator@hostname:fips> set date 201803202034.00
security-administrator@hostname:fips> set cli timestamp
```

# Configuring Inactivity Timeout Period Configuration, and Local and Remote Idle Session Termination

## IN THIS SECTION

- [Configure Session Termination](#) | 42
- [Sample Output for Local Administrative Session Termination](#) | 43
- [Sample Output for Remote Administrative Session Termination](#) | 43
- [Sample Output for User Initiated Termination](#) | 44

## Configure Session Termination

Terminate the session after the security administrator specifies inactive timeout period.

1. Set the idle timeout.

```
[edit]  
security-administrator@host:fips# set system login class security-admin idle-timeout 2
```

2. Configure the login access privileges.

```
[edit]  
security-administrator@host:fips# set system login class security-admin permissions all
```

3. Commit the configuration.

```
[edit]  
security-administrator@host:fips# commit
```

```
commit complete
```

4. Set the password.

```
[edit]  
security-administrator@host:fips# set system login user NDcPPv3-user authentication plain-  
text-password  
New password:  
Retype new password:
```

5. Define login class.

```
[edit]  
security-administrator@host:fips# set system login user NDcPPv3-user class security-admin
```

## 6. Commit the configuration.

```
[edit]
security-administrator@host:fips# commit
```

```
commit complete
```

## Sample Output for Local Administrative Session Termination

```
con host
Trying a.b.c.d...
'autologin': unknown argument ('set ?' for help).
Connected to device.example.com
Escape character is '^]'.

Type the hot key to suspend the connection: <CTRL>Z
FreeBSD/amd64 (host) (ttyu0)
login: NDcPPv3-user
Password:
Last login: Sun Feb 16 22:14:09 2025 from 10.220.196.20

--- JUNOS 24.2R2.18 Kernel 64-bit  JNPR-15.0-20240618.78e5114_buil
NDcPPv3-user@host> Warning: session will be closed in 1 minute if there is no activity
Warning: session will be closed in 10 seconds if there is no activity
Idle timeout exceeded: closing session

FreeBSD/amd64 (host) (ttyu0)
```

## Sample Output for Remote Administrative Session Termination

```
ssh NDcPPv3-user@host
Password:
Last login: Sun Feb 16 22:12:15 2025
--- JUNOS 24.2R2.18 Kernel 64-bit  JNPR-15.0-20240618.78e5114_buil
```

```
NDcPPv3-user@host> exit
```

```
Connection to host closed.
```

```
ssh NDcPPv3-user@host
```

```
Password:
```

```
Last login: Sun Feb 16 22:14:09 2025 from 10.220.196.20
```

```
--- JUNOS 24.2R2.18 Kernel 64-bit JNPR-15.0-20240618.78e5114_buil
```

```
At least one package installed on this device has limited support.
```

```
Run 'file show /etc/notices/unsupported.txt' for details.
```

```
NDcPPv3-user@host:RE:0% cli
```

```
{master:0}
```

```
NDcPPv3-user@host> Warning: session will be closed in 10 seconds if there is no activity
```

```
Idle timeout exceeded: closing session
```

```
NDcPPv3-user@host:RE:0% auto-logout
```

```
Connection to host closed.
```

## Sample Output for User Initiated Termination

```
ssh NDcPPv3-user@host
```

```
Password:
```

```
Last login: Mon Feb 17 01:17:22 2025 from 10.220.208.13
```

```
--- JUNOS 24.2R2.18 Kernel 64-bit JNPR-15.0-20240618.78e5114_buil
```

```
At least one package installed on this device has limited support.
```

```
Run 'file show /etc/notices/unsupported.txt' for details.
```

```
NDcPPv3-user@host:RE:0%
```

```
NDcPPv3-user@host:RE:0% exit
```

```
logout
```

```
Connection to host closed.
```

# 4

CHAPTER

## Configuring SSH and Console Connection

---

### IN THIS CHAPTER

- [Configuring a System Login Message and Announcement | 46](#)
  - [Configuring SSH on the Evaluated Configuration | 47](#)
  - [Limiting the Number of User Login Attempts for SSH Sessions | 49](#)
-

# Configuring a System Login Message and Announcement

A login message appears before the user logs in and an announcement appears after the user logs in. By default, no login message or announcement is displayed on the device.

To configure a system login message through console or management interface, use the following command:

```
[edit]
user@host# set system login message login-message-banner-text
```

To configure system announcement, use the following command:

```
[edit]
user@host# set system login announcement system-announcement-text
```



## NOTE:

- If the message text contains any spaces, enclose it in quotation marks.
- You can format the message using the following special characters:
  - \n—New line
  - \t—Horizontal tab
  - \'—Single quotation mark
  - \"—Double quotation mark
  - \\—Backslash

## RELATED DOCUMENTATION

| [Configuring SSH on the Evaluated Configuration](#) | 47

# Configuring SSH on the Evaluated Configuration

SSH is an allowed remote management interface in the evaluated configuration. This topic describes how to configure SSH on the device.

- Before you begin, log in with your root account on the device.

To configure SSH on the device:

1. Specify the permissible SSH host-key algorithms for the system services.

```
[edit ]
root@host# set system services ssh hostkey-algorithm ssh-ecdsa
root@host# set system services ssh hostkey-algorithm no-ssh-dss
root@host# set system services ssh hostkey-algorithm ssh-rsa
root@host# set system services ssh hostkey-algorithm no-ssh-ed25519
```

2. Specify the SSH key-exchange for Diffie-Hellman keys for the system services.

```
[edit ]
root@host# set system services ssh key-exchange ecdh-sha2-nistp256
root@host# set system services ssh key-exchange ecdh-sha2-nistp384
root@host# set system services ssh key-exchange ecdh-sha2-nistp521
```

3. Specify all the permissible message authentication code algorithms for SSHv2.

```
[edit ]

root@host# set system services ssh macs hmac-sha2-256
root@host# set system services ssh macs hmac-sha2-512
```

4. Specify the ciphers allowed for protocol version 2.

```
[edit ]
root@host# set system services ssh ciphers aes128-cbc
root@host# set system services ssh ciphers aes256-cbc
root@host# set system services ssh ciphers aes128-ctr
root@host# set system services ssh ciphers aes256-ctr
```



**NOTE:** To disable Netconf service, deactivate the netconf configurations:

```
root@host# deactivate system services netconf ssh
```



**NOTE:** To enable Netconf service, activate the netconf configurations:

```
root@host# activate system services netconf ssh
```

Supported SSH hostkey algorithm:

|           |                                    |
|-----------|------------------------------------|
| ssh-ecdsa | Allow generation of ECDSA host-key |
| ssh-rsa   | Allow generation of RSA host-key   |

Supported SSH key-exchange algorithm:

|                    |                                                 |
|--------------------|-------------------------------------------------|
| ecdh-sha2-nistp256 | The EC Diffie-Hellman on nistp256 with SHA2-256 |
| ecdh-sha2-nistp384 | The EC Diffie-Hellman on nistp384 with SHA2-384 |
| ecdh-sha2-nistp521 | The EC Diffie-Hellman on nistp521 with SHA2-512 |

Supported MAC algorithm:

|               |                                                   |
|---------------|---------------------------------------------------|
| hmac-sha2-256 | Hash-based MAC using Secure Hash Algorithm (SHA2) |
| hmac-sha2-512 | Hash-based MAC using Secure Hash Algorithm (SHA2) |

Supported SSH ciphers algorithm:

|            |                                        |
|------------|----------------------------------------|
| aes128-cbc | 128-bit AES with Cipher Block Chaining |
| aes128-ctr | 128-bit AES with Counter Mode          |
| aes256-cbc | 256-bit AES with Cipher Block Chaining |
| aes256-ctr | 256-bit AES with Counter Mode          |

## RELATED DOCUMENTATION

[Limiting the Number of User Login Attempts for SSH Sessions](#) | 49

# Limiting the Number of User Login Attempts for SSH Sessions

An administrator may login remotely to a device through SSH. Administrator credentials are stored locally on the device. If the administrator presents a valid username and password, access to the Target of Evaluation (TOE) is granted. If the credentials are invalid, the TOE allows the authentication to be retried after an interval that starts after 1 second and increases exponentially. If the number of authentication attempts exceed the configured maximum, no authentication attempts are accepted for a configured time interval. When the interval expires, authentication attempts are again accepted.

You configure the amount of time the device gets locked after failed attempts. The amount of time in minutes before the user can attempt to log in to the device after being locked out due to the number of failed login attempts specified in the `tries-before-disconnect` statement. When a user fails to correctly login after the number of allowed attempts specified by the `tries-before-disconnect` statement, the user must wait the configured amount of minutes before attempting to log in to the device again. During this lockout-period the remote session user still have access to the TOE through the console as the root user.

The `lockout-period` must be greater than zero. The range at which you can configure the `lockout-period` is one through 43,200 minutes.

```
[edit system login]
user@host# set retry-options lockout-period number
```

You can configure the device to limit the number of attempts to enter a password while logging through SSH. Using the following command, the connection.

```
[edit system login]
user@host# set retry-options tries-before-disconnect number
```

Here, `tries-before-disconnect` is the number of times a user can attempt to enter a password when logging in. The connection closes if a user fails to log in after the number specified. The range is from 2 through 10, and the default value is 3.

The local administrator access will be maintained even if the remote administration is made permanently or temporarily unavailable due to the multiple failed login attempts. The console login for local administration will be available to the users during the lockout period.

You can also configure a delay, in seconds, before a user can try to enter a password after a failed attempt.

```
[edit system login]
user@host# set retry-options backoff-threshold number
```

Here, backoff-threshold is the threshold for the number of failed login attempts before the user experiences a delay in being able to enter a password again. The range is from 1 through 3, and the default value is 2 seconds.

In addition, the device can be configured to specify the threshold for the number of failed attempts before the user experiences a delay in entering the password again.

```
[edit system login]
user@host# set retry-options backoff-factor number
```

Here, backoff-factor is the length of time, in seconds, before a user can attempt to log in after a failed attempt. The delay increases by the value specified for each subsequent attempt after the threshold. The range is from 5 through 10, and the default value is 5 seconds.

You can control user access through SSH. By configuring `ssh root-login deny`, you can ensure the root account remains active and continues to have local administrative privileges to the TOE even if other remote users are logged off.

```
[edit system]
user@host# set services ssh root-login deny
```

The SSH2 protocol provides secure terminal sessions utilizing the secure encryption. The SSH2 protocol enforces running the key-exchange phase and changing the encryption and integrity keys for the session. Key exchange is done periodically, after specified seconds or after specified bytes of data have passed over the connection. You can configure thresholds for SSH rekeying, FCS\_SSHS\_EXT.1.8 and FCS\_SSHC\_EXT.1.8. The TSF ensures that within the SSH connections the same session keys are used

for a threshold of no longer than one hour, and no more than one gigabyte of the transmitted data. When either of the thresholds are reached, a rekey must be performed.

```
[edit system]
security-administrator@host:fips# set services ssh rekey time-limit number
```

Time limit before renegotiating session keys is 1 through 1440 minutes.

```
[edit system]
security-administrator@host:fips# set services ssh rekey data-limit number
```

Data limit before renegotiating session keys is 51200 through 4294967295 byte.



**NOTE:** For SSH connection being unintentionally broken, we need to re-initiate the SSH connection to log in back to TOE.

## RELATED DOCUMENTATION

| [Configuring SSH on the Evaluated Configuration](#) | 47

# 5

CHAPTER

## Configuring the Remote Syslog Server

---

### IN THIS CHAPTER

- [Syslog Server Configuration on a Linux System | 53](#)
-

# Syslog Server Configuration on a Linux System

## IN THIS SECTION

- [Configuring Event Logging to a Remote Server when Initiating the Connection from the Remote Server](#)  
| 53

A secure Junos OS environment requires auditing of events and storing them in a local audit file. The recorded events are simultaneously sent to an external syslog server. A syslog server receives the syslog messages streamed from the device. The syslog server must have an SSH client with NETCONF support configured to receive the streamed syslog messages.

The NDcPP logs capture the following events:

- Committed changes
- System startup
- Login and logout of users
- Failure to establish an SSH session
- Establishment or termination of an SSH session
- Changes to the system time
- Initiation of a system update

## Configuring Event Logging to a Remote Server when Initiating the Connection from the Remote Server

The following procedure describes the steps to configure event logging to a remote server when the SSH connection to the TOE is initiated from the remote system log server.

1. Generate an RSA public key on the remote syslog server.

```
$ ssh-keygen -b 2048 -t rsa -C 'syslog-monitor key pair' -f ~/.ssh/syslog-monitor
```

You will be prompted to enter the desired passphrase. The storage location for the `syslog-monitor` key pair is displayed.

2. On the TOE, create a class named `monitor` that has permission to trace events.

```
[edit]
user@host# set system login class monitor permissions trace
```

3. Create a user named `syslog-mon` with the class `monitor`, and with authentication that uses the `syslog-monitor` key pair from the key pair file located on the remote syslog server.

```
[edit]
user@host# set system login user syslog-mon class monitor authentication ssh-rsa "ssh-rsa
xxxxx syslog-monitor key pair"
```

4. Set up NETCONF with SSH.

```
[edit]
user@host# set system services netconf ssh
```

5. Configure syslog to log all the messages at `/var/log/messages`.

```
[edit]
user@host# set system syslog file messages any any
user@host# commit
```

6. On the remote system log server, start up the SSH agent. The start up is required to simplify the handling of the `syslog-monitor` key.

```
$ eval `ssh-agent`
```

7. On the remote syslog server, add the `syslog-monitor` key pair to the SSH agent.

```
$ ssh-add ~/.ssh/syslog-monitor
```

You will be prompted to enter the desired passphrase. Enter the same passphrase used in Step 1.

8. After logging in to the `external_syslog_server` session, establish a tunnel to the device and start NETCONF.

```
$ ssh syslog-mon@NDcPP_TOE -s netconf > test.out
```

9. After NETCONF is established, configure a system log events message stream. This RPC will cause the NETCONF service to start transmitting messages over the SSH connection that is established.

```
<rpc><get-syslog-events><stream>messages</stream></get-syslog-events></rpc>
```

10. The examples for syslog messages are listed below. Monitor the event log generated for admin actions on TOE as received on the syslog server. Examine the traffic that passes between the audit server and the TOE, observing that these data are not viewed during this transfer, and that they are successfully received by the audit server. Match the logs between local event and the remote event logged in a syslog server and record the particular software (such as name, version, and so on) used on the audit server during testing.

The following output shows test log results for syslog-server.

```
host@ssh-keygen -b 2048 -t rsa -C 'syslog-monitor key pair' -f ~/.ssh/syslog-monitor
Generating public/private rsa key pair.
Enter passphrase (empty for no passphrase):
Enter same passphrase again:
Your identification has been saved in /home/host/.ssh/syslog-monitor.
Your public key has been saved in /home/host/.ssh/syslog-monitor.pub.
The key fingerprint is:
ef:75:d7:68:c5:ad:8d:6f:5e:7a:7e:9b:3d:f1:4d:3f syslog-monitor key pair
The key's randomart image is:
+--[ RSA 2048 ]-----+
|           |
|           |
|           |
|          ..|
|         S  +|
|        .   Bo|
|       . . *.X|
|      . . o E@|
|     .   .BX|
+-----+
[host@nms5-vm-linux2 ~]$ cat /home/host/.ssh/syslog-monitor.pub
ssh-rsa
```

```

AAAAAB3NzaC1yc2EAAAADAQABAAQCrUREJUBpjwAoIgRrGy9zgt+
D2pikk3Q/Wdf8I5vr+njeqJhCx2bUAkrRbYXNILQQAzb7kLfi/8TqqL
eon4HOP2e6oCSorKdx/GrOTzLONL4fh0EyuSAk8bs5JuwWNBuokV025
gzpGFsBusGn1j6wqqJ/sjFsMmfxyCkbY+pUWb8m1/A9YjOFT+6esw+9S
tF6Gbg+VpbYYk/0day4z+z7tQHRFSrxj2G92aoLiVDBLJparEMbc8w
LdSUDxmgBTMoadOmm+kreBUQjrmr6775RJn9H9YwIxK0xGm4SFnx/V14
R+lZ9RqmKH2wodIEM34K0wXEHZAzNZ01oLmaAVqT
syslog-monitor key pair
[host@nms5-vm-linux2 ~]$ eval `ssh-agent -s`
Agent pid 1453
[host@nms5-vm-linux2 ~]$ ssh-add ~/.ssh/syslog-monitor
Enter passphrase for /home/host/.ssh/syslog-monitor:
Identity added: /home/host/.ssh/syslog-monitor (/home/host/.ssh/syslog-monitor)

```

### Net configuration channel

```

host@nms5-vm-linux2 ~]$ ssh syslog-mon@starfire -s netconf

this is NDcPP test device

<!-- No zombies were killed during the creation of this user interface --
<!-- user syslog-mon, class j-monitor -><hello>
  <capabilities>
    <capability>urn:ietf:params:xml:ns:netconf:base:1.0</capability>
    <capability>urn:ietf:params:xml:ns:netconf:capability:candidate:1.0</capability>
    <capability>urn:ietf:params:xml:ns:netconf:capability:confirmed-commit:1.0</capability>
    <capability>urn:ietf:params:xml:ns:netconf:capability:validate:1.0</capability>
    <capability>urn:ietf:params:xml:ns:netconf:capability:url:1.0?protocol=http,ftp,file</
capability>
    <capability>http://xml.juniper.net/netconf/junos/1.0</capability>
    <capability>http://xml.juniper.net/dmi/system/1.0</capability>
  </capabilities>
  <session-id4129/session-id>
</hello>
]]>]]>

```

The following output shows event logs generated on the TOE that are received on the syslog server.

```

Jan 20 17:04:51 starfire sshd[4182]: error: Could not load host key: /etc/ssh/ssh_host_dsa_key
Jan 20 17:04:51 starfire sshd[4182]: error: Could not load host key: /etc/ssh/ssh_host_ecdsa_key
Jan 20 17:04:53 starfire sshd[4182]: Accepted password for sec-admin from 10.209.11.24 port

```

```
55571 ssh2
```

```
Jan 20 17:04:53 starfire mgd[4186]: UI_AUTH_EVENT: Authenticated user 'sec-admin' at permission level 'j-administrator'
```

```
Jan 20 17:04:53 starfire mgd[4186]: UI_LOGIN_EVENT: User 'sec-admin' login, class 'j-administrator' [4186], ssh-connection '10.209.11.24 55571 10.209.14.92 22', client-mode 'cli'
```

## Net configuration channel

```
host@nms5-vm-linux2 ~]$ ssh syslog-mon@starfire -s netconf
```

```
this is NDcPP test device
```

```
<!-- No zombies were killed during the creation of this user interface --
```

```
<!-- user syslog-mon, class j-monitor -><hello>
```

```
<capabilities>
```

```
<capability>urn:ietf:params:xml:ns:netconf:base:1.0</capability>
```

```
<capability>urn:ietf:params:xml:ns:netconf:capability:candidate:1.0</capability>
```

```
<capability>urn:ietf:params:xml:ns:netconf:capability:confirmed-commit:1.0</capability>
```

```
<capability>urn:ietf:params:xml:ns:netconf:capability:validate:1.0</capability>
```

```
<capability>urn:ietf:params:xml:ns:netconf:capability:url:1.0?protocol=http,ftp,file</
```

```
capability>
```

```
<capability>http://xml.juniper.net/netconf/junos/1.0</capability>
```

```
<capability>http://xml.juniper.net/dmi/system/1.0</capability>
```

```
</capabilities>
```

```
<session-id4129/session-id>
```

```
</hello>
```

```
]]>]]>
```

The following output shows that the local syslogs and remote syslogs received were similar.

```
Local :
```

```
an 20 17:09:30 starfire mgd[4186]: UI_COMMIT_PROGRESS: Commit operation in progress: Redundancy interface management process checking new configuration
```

```
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_START: Starting child '/usr/sbin/rdd'
```

```
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_STATUS: Cleanup child '/usr/sbin/rdd', PID 4317, status 0
```

```
Jan 20 17:09:30 starfire mgd[4186]: UI_COMMIT_PROGRESS: Commit operation in progress: Dynamic flow capture service checking new configuration
```

```
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_START: Starting child '/usr/sbin/dfcd'
```

```
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_STATUS: Cleanup child '/usr/sbin/dfcd', PID 4318, status 0
```

```
Jan 20 17:09:30 starfire mgd[4186]: UI_COMMIT_PROGRESS: Commit operation in progress:
```

```

Connectivity fault management process checking new configuration
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_START: Starting child '/usr/sbin/cfmd'
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_STATUS: Cleanup child '/usr/sbin/cfmd', PID 4319,
status 0
Jan 20 17:09:30 starfire mgd[4186]: UI_COMMIT_PROGRESS: Commit operation in progress: Layer 2
address flooding and learning process checking new configuration
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_START: Starting child '/usr/sbin/l2ald'
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_STATUS: Cleanup child '/usr/sbin/l2ald', PID 4320,
status 0
Jan 20 17:09:30 starfire mgd[4186]: UI_COMMIT_PROGRESS: Commit operation in progress: Layer 2
Control Protocol process checking new configuration
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_START: Starting child '/usr/sbin/l2cpd'
Jan 20 17:09:30 starfire l2cp[4321]: Initializing PNAC state machines
Jan 20 17:09:30 starfire l2cp[4321]: Initializing PNAC state machines complete
Jan 20 17:09:30 starfire l2cp[4321]: Initialized 802.1X module and state machinesJan 20
17:09:30 starfire l2cp[4321]: Read access profile () config
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_STATUS: Cleanup child '/usr/sbin/l2cpd', PID 4321,
status 0
Jan 20 17:09:30 starfire mgd[4186]: UI_COMMIT_PROGRESS: Commit operation in progress: Multicast
Snooping process checking new configuration
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_START: Starting child '/usr/sbin/mcsnoopd'
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_STATUS: Cleanup child '/usr/sbin/mcsnoopd', PID
4325, status 0
Jan 20 17:09:30 starfire mgd[4186]: UI_COMMIT_PROGRESS: Commit operation in progress: commit
wrapup...
Jan 20 17:09:30 starfire mgd[4186]: UI_COMMIT_PROGRESS: Commit operation in progress:
activating '/var/etc/ntp.conf'
Jan 20 17:09:30 starfire mgd[4186]: UI_COMMIT_PROGRESS: Commit operation in progress: start ffp
activate
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_START: Starting child '/usr/sbin/ffp'
Jan 20 17:09:30 starfire ffp[4326]: "dynamic-profiles": No change to profiles
.....

```

Remote :

```

an 20 17:09:30 starfire mgd[4186]: UI_COMMIT_PROGRESS: Commit operation in progress: Redundancy
interface management process checking new configuration
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_START: Starting child '/usr/sbin/rdd'
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_STATUS: Cleanup child '/usr/sbin/rdd', PID 4317,
status 0
Jan 20 17:09:30 starfire mgd[4186]: UI_COMMIT_PROGRESS: Commit operation in progress: Dynamic
flow capture service checking new configuration

```

```

Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_START: Starting child '/usr/sbin/dfcd'
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_STATUS: Cleanup child '/usr/sbin/dfcd', PID 4318,
status 0
Jan 20 17:09:30 starfire mgd[4186]: UI_COMMIT_PROGRESS: Commit operation in progress:
Connectivity fault management process checking new configuration
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_START: Starting child '/usr/sbin/cfmd'
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_STATUS: Cleanup child '/usr/sbin/cfmd', PID 4319,
status 0
Jan 20 17:09:30 starfire mgd[4186]: UI_COMMIT_PROGRESS: Commit operation in progress: Layer 2
address flooding and learning process checking new configuration
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_START: Starting child '/usr/sbin/l2ald'
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_STATUS: Cleanup child '/usr/sbin/l2ald', PID 4320,
status 0
Jan 20 17:09:30 starfire mgd[4186]: UI_COMMIT_PROGRESS: Commit operation in progress: Layer 2
Control Protocol process checking new configuration
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_START: Starting child '/usr/sbin/l2cpd'
Jan 20 17:09:30 starfire l2cp[4321]: Initializing PNAC state machines
Jan 20 17:09:30 starfire l2cp[4321]: Initializing PNAC state machines complete
Jan 20 17:09:30 starfire l2cp[4321]: Initialized 802.1X module and state machinesJan 20
17:09:30 starfire l2cp[4321]: Read access profile () config
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_STATUS: Cleanup child '/usr/sbin/l2cpd', PID 4321,
status 0
Jan 20 17:09:30 starfire mgd[4186]: UI_COMMIT_PROGRESS: Commit operation in progress: Multicast
Snooping process checking new configuration
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_START: Starting child '/usr/sbin/mcsnoopd'
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_STATUS: Cleanup child '/usr/sbin/mcsnoopd', PID
4325, status 0
Jan 20 17:09:30 starfire mgd[4186]: UI_COMMIT_PROGRESS: Commit operation in progress: commit
wrapup...
Jan 20 17:09:30 starfire mgd[4186]: UI_COMMIT_PROGRESS: Commit operation in progress:
activating '/var/etc/ntp.conf'
Jan 20 17:09:30 starfire mgd[4186]: UI_COMMIT_PROGRESS: Commit operation in progress: start ffp
activate
Jan 20 17:09:30 starfire mgd[4186]: UI_CHILD_START: Starting child '/usr/sbin/ffp'
Jan 20 17:09:30 starfire ffp[4326]: "dynamic-profiles": No change to profiles
.....

```

# 6

CHAPTER

## Configuring Audit Log Options

---

### IN THIS CHAPTER

- [Configuring Audit Log Options in the Evaluated Configuration | 61](#)
  - [Sample Code Audits of Configuration Changes | 62](#)
-

# Configuring Audit Log Options in the Evaluated Configuration

## IN THIS SECTION

- [Configuring Audit Log Options | 61](#)

The following section describes how to configure audit log options in the evaluated configuration.

## Configuring Audit Log Options

To configure audit log options for your devices:

1. Specify the number of files to be archived in the system logging facility.

```
[edit system syslog]
root@host#set archive files 2
```

2. Specify the file in which to log data.

```
[edit system syslog]
root@host#set file Audit_logs any any
```

3. Specify the size of files to be archived.

```
[edit system syslog]
root@host#set file Audit_logs archive size 10m
```

4. (Optional) Configure explicit-priority or structured-data option depending on the user requirement.

```
[edit system syslog]
root@host#set file Audit_logs explicit-priority
```

Or

```
[edit system syslog]
root@host#set file Audit_logs structured-data
```

## RELATED DOCUMENTATION

| [Sample Code Audits of Configuration Changes](#) | 62

# Sample Code Audits of Configuration Changes

This sample code audits all changes to the configuration secret data and sends the logs to a file named **messages**:

```
[edit system]
syslog {
  file messages {
    authorization info;
    change-log info;
    interactive-commands info;
  }
}
```

This sample code expands the scope of the minimum audit to audit all changes to the configuration, not just secret data, and sends the logs to a file named **messages**:

```
[edit system]
syslog {
  file messages {
    any any;
    authorization info;
    change-log any;
    interactive-commands info;
    kernel info;
    pfe info;
  }
}
```

```

    }
}

```

### Example: System Logging of Configuration Changes

This example shows a sample configuration and makes changes to users and secret data.

```

[edit system]
location {
    country-code US;
    building B1;
}
...
login {
    message "UNAUTHORIZED USE OF THIS ROUTER\n\tIS STRICTLY PROHIBITED!";
    user crypto-officer {
        uid 2000;
        class security-admin;
        authentication {
            encrypted-password "$ABC123";
            # SECRET-DATA
        }
    }
    password {
        format sha512;
    }
}
radius-server 192.0.2.15 {
    secret "$ABC123" # SECRET-DATA
}
services {
    ssh;
}
syslog {
    user *{
        any emergency;
    }
    file messages {
        any notice;
        authorization info;
    }
    file interactive-commands {

```

```

        interactive-commands any;
    }
}
...
...

```

The new configuration changes the secret data configuration statements and adds a new user.

```

user@host# show | compare
[edit system login user admin authentication]
-   encrypted-password "$ABC123"; # SECRET-DATA
+   encrypted-password "$ABC123"; # SECRET-DATA
[edit system login]
+   user admin2 {
+       uid 2001;
+       class read-only;
+       authentication {
+           encrypted-password "$ABC123";
+               # SECRET-DATA
+       }
+   }
[edit system radius-server 192.0.2.15]
-   secret "$ABC123"; # SECRET-DATA
+   secret "$ABC123"; # SECRET-DATA

```

[Table 3 on page 65](#) shows sample for syslog auditing for NDcPPv3.0e:

Table 3: Auditable Events

| Requirement | Auditable Events | Additional Audit Record Contents | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |
|-------------|------------------|----------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| FAU_GEN.1   | None             | None                             | <p>May 19 21:43:16 host eventd[7841]:<br/>SYSTEM_OPERATIONAL: System is operational</p> <p>May 19 21:43:17 host jlaunchd[8318]: Found pid 7842 for already running process: eventd</p> <p>May 8 23:29:38 mgd[19298]:<br/>UI_AUTH_EVENT: Authenticated user 'crypto-officer' assigned to class 'j-super-user'</p> <p>May 8 23:29:38 mgd[19298]:<br/>UI_LOGIN_EVENT: User 'crypto-officer' login, class 'j-super-user' [19298], ssh-connection ", client-mode 'cli'</p> <p>May 8 23:30:49 mgd[19298]:<br/>UI_DBASE_LOGIN_EVENT: User 'crypto-officer' entering configuration mode</p> <p>May 8 23:31:06 mgd[19298]:<br/>UI_CMDLINE_READ_LINE: User 'crypto-officer', command 'set system login message "this is a ndcpp test box" '</p> |

Table 3: Auditable Events (*Continued*)

| Requirement | Auditable Events | Additional Audit Record Contents | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
|-------------|------------------|----------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|             |                  |                                  | <p>May 8 23:31:09<br/>mgd[19298]:<br/>UI_CMDLINE_READ_LINE: User 'crypto-officer',<br/>command 'commit '</p> <p>May 8 23:35:06<br/>mgd[20830]:<br/>UI_CMDLINE_READ_LINE: User 'crypto-officer',<br/>command 'start shell '</p> <p>May 8 23:35:31 ssh-keygen[20913]:<br/>Generated SSH key<br/>file /var/home/crypto-officer/.ssh/id_rsa.pub<br/>with fingerprint<br/>SHA256:iqrLYhPTXD4K<br/>hYOeuL<br/>+tD8odyYUb/G2O<br/>+Fzk9lnzZeg</p> <p>May 8 23:42:38<br/>mgd[22907]:<br/>UI_CFG_AUDIT_SET:<br/>User 'crypto-officer' set:<br/>[system root-authentication]<br/>unconfigured -- "plain-text-password"</p> <p>May 8 23:42:44<br/>mgd[22907]:<br/>UI_CMDLINE_READ_LINE: User 'crypto-officer',<br/>command 'set system<br/>root-authentication<br/>plain-text-password '</p> |

Table 3: Auditable Events (*Continued*)

| Requirement | Auditable Events | Additional Audit Record Contents | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |
|-------------|------------------|----------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|             |                  |                                  | <p>May 8 23:42:46<br/>mgd[22907]:<br/>UI_CMDLINE_READ_LINE: User 'crypto-officer',<br/>command 'commit '</p> <p>May 8 23:42:46<br/>mgd[22907]:<br/>UI_COMMIT: User<br/>'crypto-officer'<br/>requested 'commit'<br/>operation (comment:<br/>none)</p> <p>May 8 23:42:46<br/>mgd[22907]:<br/>UI_COMMIT_PROGRESS: Commit operation in<br/>progress: Obtaining lock<br/>for commit</p> <p>May 8 23:42:46<br/>mgd[22907]:<br/>UI_COMMIT_PROGRESS: Commit operation in<br/>progress: updating<br/>commit revision</p> <p>May 8 23:42:46<br/>mgd[22907]:<br/>UI_COMMIT_PROGRESS: Commit operation in<br/>progress: UI extensions<br/>feature is not configured</p> <p>May 8 23:42:46<br/>mgd[22907]:<br/>UI_COMMIT_PROGRESS: Commit operation in<br/>progress: UI change-<br/>notification feature is<br/>not configured</p> |

**Table 3: Auditable Events** *(Continued)*

| Requirement | Auditable Events | Additional Audit Record Contents | How event generated                                                                                                                |
|-------------|------------------|----------------------------------|------------------------------------------------------------------------------------------------------------------------------------|
|             |                  |                                  | May 8 23:42:46<br>mgd[22907]:<br>UI_COMMIT_PROGRES<br>S: Commit operation in<br>progress: Started<br>running translation<br>script |

Table 3: Auditable Events *(Continued)*

| Requirement | Auditable Events | Additional Audit Record Contents | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
|-------------|------------------|----------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| FAU_GEN.2   | None             | None                             | <p>May 8 23:29:38<br/>mgd[19298]:<br/>UI_AUTH_EVENT:<br/>Authenticated user<br/>'crypto-officer' assigned<br/>to class 'j-super-user'</p> <p>May 8 23:29:38<br/>mgd[19298]:<br/>UI_LOGIN_EVENT: User<br/>'crypto-officer' login,<br/>class 'j-super-user'<br/>[19298], ssh-connection<br/>, client-mode 'cli'</p> <p>May 8 23:30:49<br/>mgd[19298]:<br/>UI_DBASE_LOGIN_EVENT:<br/>User 'crypto-officer'<br/>entering configuration<br/>mode</p> <p>May 8 23:31:06<br/>mgd[19298]:<br/>UI_CMDLINE_READ_LINE:<br/>User 'crypto-officer',<br/>command 'set system<br/>login message "this is a<br/>ndcpp test box" '</p> <p>May 8 23:31:09<br/>mgd[19298]:<br/>UI_CMDLINE_READ_LINE:<br/>User 'crypto-officer',<br/>command 'commit '</p> <p>May 8 23:35:06<br/>mgd[20830]:<br/>UI_CMDLINE_READ_LINE:<br/>User 'crypto-officer',<br/>command 'start shell '</p> |

Table 3: Auditable Events (*Continued*)

| Requirement | Auditable Events | Additional Audit Record Contents | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |
|-------------|------------------|----------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|             |                  |                                  | <p>May 8 23:35:31 ssh-keygen[20913]:<br/>Generated SSH key file /var/home/crypto-officer/.ssh/id_rsa.pub with fingerprint<br/>SHA256:iqrLYhPTXD4KhYOeuL<br/>+tD8odyYUb/G2O<br/>+Fzk9lnzZeg</p> <p>May 8 23:42:38<br/>mgd[22907]:<br/>UI_CFG_AUDIT_SET:<br/>User 'crypto-officer' set:<br/>[system root-authentication]<br/>unconfigured -- "plain-text-password"</p> <p>May 8 23:42:44<br/>mgd[22907]:<br/>UI_CMDLINE_READ_LINE: User 'crypto-officer',<br/>command 'set system root-authentication plain-text-password '</p> <p>May 8 23:42:46<br/>mgd[22907]:<br/>UI_CMDLINE_READ_LINE: User 'crypto-officer',<br/>command 'commit '</p> <p>May 8 23:42:46<br/>mgd[22907]:<br/>UI_COMMIT: User 'crypto-officer'<br/>requested 'commit' operation (comment: none)</p> |

Table 3: Auditable Events (*Continued*)

| Requirement | Auditable Events | Additional Audit Record Contents | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
|-------------|------------------|----------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|             |                  |                                  | <p>May 8 23:42:46<br/>mgd[22907]:<br/>UI_COMMIT_PROGRES<br/>S: Commit operation in progress: Obtaining lock for commit</p> <p>May 8 23:42:46<br/>mgd[22907]:<br/>UI_COMMIT_PROGRES<br/>S: Commit operation in progress: updating commit revision</p> <p>May 8 23:42:46<br/>mgd[22907]:<br/>UI_COMMIT_PROGRES<br/>S: Commit operation in progress: UI extensions feature is not configured</p> <p>May 8 23:42:46<br/>mgd[22907]:<br/>UI_COMMIT_PROGRES<br/>S: Commit operation in progress: UI change-notification feature is not configured</p> <p>May 8 23:42:46<br/>mgd[22907]:<br/>UI_COMMIT_PROGRES<br/>S: Commit operation in progress: Started running translation script</p> |

Table 3: Auditable Events *(Continued)*

| Requirement   | Auditable Events                       | Additional Audit Record Contents                               | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
|---------------|----------------------------------------|----------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| FAU_STG_EXT.1 | Configuration of local audit settings. | Identity of account making changes to the audit configuration. | <p>May 19 22:11:47 host mgd[13786]:<br/>UI_CFG_AUDIT_SET: User 'crypto-officer' set: [groups global system syslog file security user] unconfigured -- "any"</p> <p>May 19 22:11:47 host mgd[13786]:<br/>UI_CMDLINE_READ_LINE: User 'crypto-officer', command 'set user any '</p> <p>May 19 22:11:49 host mgd[13786]:<br/>UI_CMDLINE_READ_LINE: User 'crypto-officer', command 'commit '</p> <p>May 19 22:11:49 host mgd[13786]:<br/>UI_COMMIT: User 'crypto-officer' requested 'commit' operation (comment: none)</p> <p>May 19 22:11:49 host mgd[13786]:<br/>UI_COMMIT_PROGRESS: Commit operation in progress: Obtaining lock for commit</p> <p>May 19 22:11:49 host mgd[13786]:<br/>UI_COMMIT_PROGRESS: Commit operation in progress: updating commit revision</p> |

**Table 3: Auditable Events (Continued)**

| Requirement              | Auditable Events | Additional Audit Record Contents | How event generated |
|--------------------------|------------------|----------------------------------|---------------------|
| FAU_STG.1                | None             | None                             |                     |
| FCS_CKM.1                | None             | None                             |                     |
| FCS_CKM.2                | None             | None                             |                     |
| FCS_CKM.4                | None             | None                             |                     |
| FCS_COP.1/DataEncryption | None             | None                             |                     |
| FCS_COP.1/SigGen         | None             | None                             |                     |
| FCS_COP.1/Hash           | None             | None                             |                     |
| FCS_COP.1/KeyedHash      | None             | None                             |                     |
| FCS_RBG_EXT.1            | None             | None                             |                     |

Table 3: Auditable Events *(Continued)*

| Requirement   | Auditable Events | Additional Audit Record Contents | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |
|---------------|------------------|----------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| FIA_PMG_EXT.1 | None             | None                             | <p>Passwords shall be able to be composed of any combination of upper and lower</p> <p>case letters, numbers and the following special characters: [selection: "!", "@",</p> <p>"#", "\$", "%", "^", "&amp;", "**",</p> <p>("", "), [assignment: other characters]];</p> <p>crypto-</p> <p>officer@host:fips# set</p> <p>system login user</p> <p>crypto-officer</p> <p>authentication plain-</p> <p>text-password</p> <p>New password:</p> <p>error: minimum</p> <p>password length is 10</p> <p>error: require use of 3</p> <p>character sets: upper</p> <p>lower digit punctuation</p> <p>other</p> |

Table 3: Auditable Events (*Continued*)

| Requirement   | Auditable Events                                        | Additional Audit Record Contents         | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |
|---------------|---------------------------------------------------------|------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| FIA_UIA_EXT.1 | All use of identification and authentication mechanism. | Origin of the attempt (e.g., IP address) | <p>Successful Local Login</p> <p>Banner example log:</p> <p>login:</p> <p>This is a protected device.</p> <p>If you are not authorized to connect, please disconnect immediately.</p> <p>Please contact 111-111-111 or ab123@123.net for assistance.</p> <p>FreeBSD/i386 (hostname) (ttyu0)</p> <p>login:</p> <p>386 (host) (ttyu0)</p> <p>login: cli<br/>Password:<br/>Login incorrect<br/>login:<br/>login: root<br/>Password:<br/>Last login: Tue May 13 22:38:08 on ttyu0</p> <p>--- JUNOS 24.2R2.10<br/>Kernel 64-bit _<br/>At least one package installed on this device has limited support.<br/>Run 'file show /etc/</p> |

Table 3: Auditable Events (*Continued*)

| Requirement | Auditable Events | Additional Audit Record Contents | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |
|-------------|------------------|----------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|             |                  |                                  | <p>notices/unsupported.txt' for details.<br/> root@host-01:RE:0% cli {master:0}<br/> root@host:fips&gt;</p> <p>Jan 3 09:59:36<br/> login[7637]:<br/> LOGIN_INFORMATION:<br/> User root logged in from host [unknown] on device ttyu0</p> <p>Jan 3 09:59:36<br/> login[7637]:<br/> LOGIN_ROOT: User root logged in as root from host [unknown] on device ttyu0</p> <p>Unsuccessful Local Login</p> <p>Jan 3 09:57:52<br/> login[7637]:<br/> LOGIN_PAM_AUTHENTICATION_ERROR: Failed password for user root</p> <p>Jan 3 09:57:52<br/> login[7637]:<br/> LOGIN_FAILED: Login failed for user root from host ttyu0</p> <p>Successful Remote Login</p> <p>Jan 3 09:32:07<br/> mgd[47035]:<br/> UI_AUTH_EVENT:<br/> Authenticated user 'test1' assigned to class</p> |

Table 3: Auditable Events (Continued)

| Requirement            | Auditable Events                        | Additional Audit Record Contents | How event generated                                                                                                                                                                                                                                                                                                     |
|------------------------|-----------------------------------------|----------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|                        |                                         |                                  | <p>'j-read-only' Jan 3 09:32:07 mgd[47035]: UI_LOGIN_EVENT: User 'test1' login, class 'j-read-only' [47035], ssh-connection '10.1.5.153 36784 10.1.2.68 22', client-mode 'cli'</p> <p>Unsuccessful Remote Login</p> <p>Jan 3 09:26:56 sshd: SSHD_LOGIN_FAILED: Login failed for user 'test1' from host '10.1.5.153'</p> |
| FIA_UAU.7              | None                                    | None                             |                                                                                                                                                                                                                                                                                                                         |
| FMT_MOF.1/ManualUpdate | Any attempt to initiate a manual update | None                             | <p>mgd[23878]: UI_CMDLINE_READ_LINE: User 'root', command 'request system software add /var/tmp/junos-install-ex-x86-64-24.2R2.tgz</p>                                                                                                                                                                                  |
| FMT_MTD.1/CoreData     | None                                    | None                             |                                                                                                                                                                                                                                                                                                                         |
| FMT_SMF.1              | All management activities of TSF data   | None                             | Refer to the audit events listed in this table.                                                                                                                                                                                                                                                                         |
| FMT_SMR.2              | None                                    | None                             |                                                                                                                                                                                                                                                                                                                         |
| FPT_SKP_EXT.1          | None                                    | None                             |                                                                                                                                                                                                                                                                                                                         |

Table 3: Auditable Events (*Continued*)

| Requirement   | Auditable Events                                                                 | Additional Audit Record Contents | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
|---------------|----------------------------------------------------------------------------------|----------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| FPT_APW_EXT.1 | None                                                                             | None                             |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |
| FPT_TUD_EXT.1 | Initiation of update;<br>result of the update<br>attempt (success or<br>failure) | None                             | <p>mgd[23878]:<br/>UI_CMDLINE_READ_LI<br/>NE: User 'root',<br/>command 'request<br/>system software<br/>add /var/tmp/junos-<br/>install-ex-<br/>x86-64-24.2R2.tgz</p> <p>root@host&gt; show log<br/>install 2025-09-19<br/>05:34:40 PDT<br/>mgd[22133]: /usr/<br/>libexec/ui/package -X<br/>update /var/tmp/fips-<br/>optest-<br/>x86-32-24.2R2.18-<br/>bsd15.tgz<br/>&lt;output&gt;<br/>Verified fips-optest-<br/>x86-32-24.2R2.18-<br/>bsd15 signed by<br/>PackageProductionECP2<br/>56_2025 method<br/>ECDSA256+SHA256<br/>&lt;/output&gt;<br/>&lt;package-result&gt;0&lt;/<br/>package-result&gt;</p> |

Table 3: Auditable Events (*Continued*)

| Requirement                                           | Auditable Events                                                      | Additional Audit Record Contents | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |
|-------------------------------------------------------|-----------------------------------------------------------------------|----------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| FTA_SSL_EXT.1 (if "terminate the session is selected) | The termination of a local session by the session lock.               | None                             | <p>user@linuxhost:~\$ssh<br/>crypto-officer@host</p> <p>login: crypto-officer</p> <p>Password:</p> <p>Last login: Tue May 13<br/>23:47:40 on ttyu0</p> <p>--- JUNOS 24.2R2<br/>Kernel 64-bit<br/>JNPR-15.0-20250502.3<br/>2ed862a0f7_</p> <p>{master:0}</p> <p>crypto-<br/>officer@host:fips&gt;</p> <p>Warning: session will be<br/>closed in 1 minute if<br/>there is no activity</p> <p>Warning: session will be<br/>closed in 10 seconds if<br/>there is no activity</p> <p>Idle timeout exceeded:<br/>closing session</p> <p>Connection to host<br/>closed.</p> <p>user@linuxhost:~\$</p> |
| FTA_SSL.3                                             | The termination of a remote session by the session locking mechanism. | None                             | <p>Jan 3 11:26:23 cli:<br/>UI_CLI_IDLE_TIMEOUT:<br/>Idle timeout for user<br/>'root' exceeded and<br/>session terminated</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |

Table 3: Auditable Events (*Continued*)

| Requirement | Auditable Events                           | Additional Audit Record Contents | How event generated                                                                                                                                                                                                                         |
|-------------|--------------------------------------------|----------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| FTA_SSL.4   | The termination of an interactive session. | None                             | <p>Local</p> <p>Jan 3 11:47:25<br/>mgd[52521]:<br/>UI_LOGOUT_EVENT:<br/>User 'root' logout</p> <p>Remote</p> <p>Jan 3 11:43:33<br/>sshd[52425]: Received<br/>disconnect from<br/>10.1.5.153 port<br/>36800:11: disconnected<br/>by user</p> |
| FTA_TAB.1   | None                                       | None                             |                                                                                                                                                                                                                                             |

Table 3: Auditable Events (*Continued*)

| Requirement | Auditable Events                                                                                                                                                                     | Additional Audit Record Contents                                                                  | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                     |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| FTP_ITC.1   | <ul style="list-style-type: none"> <li>Initiation of the trusted channel.</li> <li>Termination of the trusted channel.</li> <li>Failure of the trusted channel functions.</li> </ul> | <ul style="list-style-type: none"> <li>None</li> <li>None</li> <li>Reason for failure.</li> </ul> | <p>Initiation of the trusted path</p> <p>Jan 3 12:09:00<br/>sshd[53492]: Accepted keyboard-interactive/pam for root from 10.1.5.153 port 36802 ssh2</p> <p>Termination of the trusted path</p> <p>Jan 3 12:09:03<br/>sshd[53492]: Received disconnect from 10.1.5.153 port 36802:11: disconnected by user Jan 3 12:09:36 sshd:</p> <p>Failure of the trusted path</p> <p>SSHD_LOGIN_FAILED:<br/>Login failed for user 'root' from host '10.1.5.153'</p> |

Table 3: Auditable Events (*Continued*)

| Requirement     | Auditable Events                                                                                                                                                                           | Additional Audit Record Contents                                                                        | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                     |
|-----------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| FTP_TRP.1/Admin | <ul style="list-style-type: none"> <li>• Initiation of the trusted channel.</li> <li>• Termination of the trusted channel.</li> <li>• Failure of the trusted channel functions.</li> </ul> | <ul style="list-style-type: none"> <li>• None</li> <li>• None</li> <li>• Reason for failure.</li> </ul> | <p>Initiation of the trusted path</p> <p>Jan 3 12:09:00<br/>sshd[53492]: Accepted keyboard-interactive/pam for root from 10.1.5.153 port 36802 ssh2</p> <p>Termination of the trusted path</p> <p>Jan 3 12:09:03<br/>sshd[53492]: Received disconnect from 10.1.5.153 port 36802:11: disconnected by user Jan 3 12:09:36 sshd:</p> <p>Failure of the trusted path</p> <p>SSHD_LOGIN_FAILED:<br/>Login failed for user 'root' from host '10.1.5.153'</p> |
| FCS_SSHS_EXT.1  | None                                                                                                                                                                                       | None                                                                                                    | <p>sshd 72404 - - Unable to negotiate with 1.1.1.2 port 42168: no matching cipher found. Their offer: chacha20-poly1305@openssh.com , aes128-ctr, aes256-ctr, aes128-gcm@openssh.com, aes256-gcm@openssh.com, aes128-cbc, aes256-cbc</p>                                                                                                                                                                                                                |

Table 3: Auditable Events (*Continued*)

| Requirement   | Auditable Events                                                                                                                                                                                                                                 | Additional Audit Record Contents                                                                                                                                                                            | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
|---------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| FCS_SSH_EXT.1 | <ul style="list-style-type: none"> <li>• Failure to establish an SSH session</li> <li>• Establishment of SSH connection</li> <li>• Termination of SSH connection session</li> <li>• Dropping of packet(s) outsize defined size limits</li> </ul> | <ul style="list-style-type: none"> <li>• Reason for failure</li> <li>• Non-TOE endpoint of connection (IP address)</li> <li>• Non-TOE endpoint of connection (IP address)</li> <li>• Packet size</li> </ul> | <ul style="list-style-type: none"> <li>• <code>crypto-officer@toby-shell:~\$ ssh -o "userknownhostsfile /dev/null" crypto-officer@host</code></li> </ul> <p>Warning:<br/>Permanently added 'host,10.204.33.5' (ECDSA) to the list of known hosts.</p> <p>This is a protected device. If you are not authorized to connect, please disconnect immediately. Please contact 111-111-111 or ab123@123.net for assistance</p> <p>Password:</p> <p>Password:</p> <p>Password:</p> <p>crypto-officer@host's password:</p> <p>Received disconnect from 10.204.33.5 port 22:2: Too many password failures for crypto-officer<br/>Disconnected from 10.204.33.5 port 22</p> |

Table 3: Auditable Events (*Continued*)

| Requirement | Auditable Events | Additional Audit Record Contents | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        |
|-------------|------------------|----------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|             |                  |                                  | <p>On the TOE below syslog messages are seen:</p> <p>Sep 9 21:02:32 2025<br/>sshd:<br/>PAM_UNIX_LOC_PA<br/>SSWD_AUTH: local<br/>password<br/>authentication of<br/>user 'crypto-officer'<br/>failed</p> <p>Sep 9 21:02:32 2025<br/>sshd[33070]: error:<br/>PAM: Authentication<br/>error for crypto-<br/>officer from<br/>10.220.212.12</p> <p>Sep 9 21:02:32 2025<br/>sshd:<br/>SSHD_LOGIN_FAILE<br/>D: Login failed for<br/>user 'crypto-officer'<br/>from host<br/>'10.220.212.12'</p> <ul style="list-style-type: none"> <li>successful login :</li> </ul> <p>Last login: Tue May<br/>13 23:35:43 2025<br/>from 10.220.208.12</p> <p>--- JUNOS 24.2R2<br/>Kernel 64-bit<br/>JNPR-15.0-2025050<br/>2.32ed862a0f7_</p> <p>At least one package<br/>installed on this</p> |

Table 3: Auditable Events (*Continued*)

| Requirement          | Auditable Events      | Additional Audit Record Contents | How event generated                                                                                                                                                                                                                                                     |
|----------------------|-----------------------|----------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|                      |                       |                                  | <p>device has limited support.</p> <p>Run 'file show /etc/ notices/ unsupported.txt' for details.</p> <p>{master:0}</p> <ul style="list-style-type: none"> <li>disconnection log:</li> </ul> <p>crypto-officer@host:fips&gt; exit</p> <p>Connection to host closed.</p> |
| FMT_MOF.1/Functions  | None                  | None                             |                                                                                                                                                                                                                                                                         |
| FMT_MOF.1/Services   | None                  | None                             |                                                                                                                                                                                                                                                                         |
| FMT_MTD.1/CryptoKeys | None                  | None                             |                                                                                                                                                                                                                                                                         |
| FCS_MACSEC_EXT.1     | Session establishment | Secure Channel Identifier (SCI)  | <p>Apr 10 20:43:35 dot1xd[6622]: DOT1XD_MKA_SECURE_CHANNEL_CREATED: Macsec receive secure channel created for 64:87:88:5a:19:30 on interface xe-0/0/0</p>                                                                                                               |

Table 3: Auditable Events (*Continued*)

| Requirement      | Auditable Events                              | Additional Audit Record Contents | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
|------------------|-----------------------------------------------|----------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| FCS_MACSEC_EXT.3 | Creation and update of Secure Association Key | Creation and update times        | <p>Jan 28 10:49:16.505519<br/>macsec_is_sak_has_128<br/>bit_forced: ca context :<br/>fips-ca-1 found for ifd<br/>ge-0/0/47</p> <p>Jan 28 10:49:16.505531<br/>macsec_util_generate_sa<br/>k_hash: sak_key_bits<br/>value 256</p> <p>Jan 28 10:49:16.986810<br/>macsec_set_sa_msg_gen<br/>cfg_data: ifdx:697 iflx:0<br/>is_ifl:0 key:ge-0/0/47-<br/>SA-TX-AN-1 len:164<br/>an:1 sak-<br/>hash:21:8e:8e:c1:44:06:<br/>5a:73:93:c2:55:da:a7:2b<br/>:d2:38</p> <p>Jan 28 10:49:16.986917<br/>macsec_set_sa_msg_gen<br/>cfg_data: ifdx:697 iflx:0<br/>is_ifl:0 key:ge-0/0/47-<br/>SA-RX-AN-1 len:164<br/>an:1 sak-<br/>hash:21:8e:8e:c1:44:06:<br/>5a:73:93:c2:55:da:a7:2b<br/>:d2:38</p> |

Table 3: Auditable Events (*Continued*)

| Requirement      | Auditable Events                     | Additional Audit Record Contents          | How event generated                                                                                                                                                                                                                                                      |
|------------------|--------------------------------------|-------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| FCS_MACSEC_EXT.4 | Creation of Connectivity Association | Connectivity Association Key Names (CKNs) | <p>Sep 9 10:49:16.987221<br/>DOT1XD_MACSEC_SC_PRIMARY_CAK_IN_USE : ifd: ge-0/0/47 primary cak: 0123456789 is in-use</p> <p>Sep 9 10:49:22.058079<br/>DOT1XD_MACSEC_SC_CAK_ACTIVATED: ifd: ge-0/0/47 sci-out:F8C116409CB20001 sci-in:68228E6E96A20001 cak: 0123456789</p> |

Table 3: Auditable Events (*Continued*)

| Requirement   | Auditable Events                                                                                                            | Additional Audit Record Contents    | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
|---------------|-----------------------------------------------------------------------------------------------------------------------------|-------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| FCS_NTP_EXT.1 | <ul style="list-style-type: none"> <li>Configure of a new time server</li> <li>Removal of configured time server</li> </ul> | Identify if new/removed time server | <p>unconfiguring ntp</p> <p>Sep 14 09:53:13 2025<br/>xntpd[16061]: sig 1Sep 14 09:53:13 2025<br/>xntpd[16061]: 172.29.147.60 local addr 0.0.0.0 -&gt; &lt;null&gt;</p> <p>after configuring ntp</p> <p>Jan 1 00:00:40 2025<br/>xntpd[16061]: proto: precision = 0.126 usec (-23)<br/>Jan 1 00:00:40 2025<br/>xntpd[16061]: GGSN RE Option Set<br/>Jan 1 00:00:40 2025<br/>xntpd[16061]: Junos Key file processing<br/>Jan 1 00:00:40 2025<br/>xntpd[16061]: basedate set to 2018-08-07<br/>Jan 1 00:00:40 2025<br/>xntpd[16061]: gps base set to 2018-08-12 (week 14)<br/>Jan 1 00:00:40 2025<br/>xntpd[16061]: Listen normally on 0 v6wildcard [::]:123<br/>Jan 1 00:00:40 2025<br/>xntpd[16061]: Listen normally on 1 v4wildcard 0.0.0.0:123<br/>Jan 1 00:00:40 2025<br/>xntpd[16061]: Listen normally on 2 ggsn_vpn 128.0.0.1:123</p> |

Table 3: Auditable Events *(Continued)*

| Requirement | Auditable Events | Additional Audit Record Contents | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |
|-------------|------------------|----------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|             |                  |                                  | <p>Jan 1 00:00:40 2025<br/>xntpd[16061]:<br/>peer_config 636<br/>cast_flags 0x1</p> <p>Jan 1 00:00:40 2025<br/>xntpd[16061]: kernel<br/>reports TIME_ERROR:<br/>0x2041: Clock<br/>Unsynchronized</p> <p>Jan 1 00:00:40 2025<br/>xntpd[16061]: kernel<br/>reports TIME_ERROR:<br/>0x2041: Clock<br/>Unsynchronized</p> <p>Jan 1 00:00:44 2025<br/>mgd[85100]:<br/>UI_CMDLINE_READ_LI<br/>NE: User 'root',<br/>command 'run show<br/>system uptime local '</p> <p>Jan 1 00:00:44 2025<br/>mgd[85100]:<br/>UI_CHILD_START:<br/>Starting child '/usr/<br/>libexec/ui/ntpsync'</p> <p>Jan 1 00:00:44 2025<br/>mgd[85100]:<br/>UI_CHILD_STATUS:<br/>Cleanup child '/usr/<br/>libexec/ui/ntpsync', PID<br/>15996, status 0</p> <p>Jan 1 00:00:44 2025<br/>mgd[85100]:<br/>UI_CHILD_START:<br/>Starting child '/usr/<br/>libexec/ui/uptime'</p> <p>Jan 1 00:00:44 2025<br/>mgd[85100]:<br/>UI_CHILD_STATUS:<br/>Cleanup child '/usr/</p> |

Table 3: Auditable Events (*Continued*)

| Requirement | Auditable Events | Additional Audit Record Contents | How event generated                                                                                                                                                                                                        |
|-------------|------------------|----------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|             |                  |                                  | libexec/ui/uptime', PID<br>16003, status 0<br>Sep 14 09:58:17 2025<br>xntpd[16061]: ntpd:<br>time reset<br>+22150650.528988 s<br>Sep 14 09:58:17 2025<br>xntpd:<br>NTPD_CHANGED_TIM<br>E: time reset<br>+22150650.528988 s |

Table 3: Auditable Events (*Continued*)

| Requirement | Auditable Events                                      | Additional Audit Record Contents          | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |
|-------------|-------------------------------------------------------|-------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| FIA_AFL.1.1 | Unsuccessful login attempts limit is met or exceeded. | Origin of the attempt (e.g., IP address). | <p>May 14 03:41:14 sshd[9673]: error: PAM: Authentication error for crypto-officer from 10.220.208.12</p> <p>May 14 03:41:14 sshd: SSHD_LOGIN_FAILED: Login failed for user 'crypto-officer' from host '10.220.208.12'</p> <p>May 14 03:41:25 sshd: PAM_UNIX_LOC_PASSWD_AUTH: local password authentication of user 'crypto-officer' failed</p> <p>May 14 03:41:25 sshd: PAM_USER_LOCK_USE R: (pam_sm_authenticate): DEBUG: PAM_USER: crypto-officer</p> <p>May 14 03:41:25 sshd: PAM_USER_LOCK_UPD_LOCK_ATTEMPTS: (pam_sm_authenticate): DEBUG: Updating lock-attempts of user: crypto-officer attempts: 4</p> <p>May 14 03:41:25 sshd: LIBJNX_LOGIN_ACCOUNT_LOCKED: Account for user 'crypto-officer' has been locked out from logins</p> |

Table 3: Auditable Events (*Continued*)

| Requirement | Auditable Events | Additional Audit Record Contents | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
|-------------|------------------|----------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|             |                  |                                  | <p>May 14 03:41:25<br/>sshd[9673]: Failed<br/>password for crypto-<br/>officer from<br/>10.220.208.12 port<br/>37949 ssh2</p> <p>May 14 03:41:45 sshd:<br/>SSHD_LOGIN_ATTEMP<br/>TS_THRESHOLD:<br/>Threshold for<br/>unsuccessful<br/>authentication attempts<br/>(4) reached by user<br/>'crypto-officer'</p> <p>May 14 03:41:45<br/>sshd[9673]:<br/>Disconnecting<br/>authenticating user<br/>crypto-officer<br/>10.220.208.12 port<br/>37949: Too many<br/>password failures for<br/>crypto-officer [preauth]</p> |

Table 3: Auditable Events (*Continued*)

| Requirement | Auditable Events                                      | Additional Audit Record Contents          | How event generated                                                                                                                                                                                                                                                                                                                                                   |
|-------------|-------------------------------------------------------|-------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| FIA_AFL.1.2 | Unsuccessful login attempts limit is met or exceeded. | Origin of the attempt (e.g., IP address). | <p>account is unlocked:</p> <p>May 14 03:46:54 sshd: PAM_USER_LOCK_USE R: (pam_sm_authenticate): DEBUG: PAM_USER: crypto-officer</p> <p>May 14 03:46:54 sshd: PAM_USER_LOCK_USE R: (pam_sm_acct_mgmt): DEBUG: PAM_USER: crypto-officer</p> <p>May 14 03:46:54 sshd: LIBJNX_LOGIN_ACCOUNT_UNLOCKED: Account for user 'crypto-officer' has been unlocked for logins</p> |
| FPT_RPL.1   | Detected replay attempt                               | None                                      | <p>Apr 15 10:05:16.142910 MKA actor #0 received duplicate or delayed PDU</p> <p>Apr 15 10:05:16.142932 MKA actor #0 received MKPDU, SCI 3C:94:D5:A0:A0:07/1, MI 27:D7:9F:97:53:CF:EF:86:00:52:C1:78, MN 1530</p>                                                                                                                                                      |

Table 3: Auditable Events (*Continued*)

| Requirement   | Auditable Events                                                                                                                                                                                           | Additional Audit Record Contents                                                                                                                         | How event generated                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |
|---------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| FPT_STM_EXT.1 | Discontinuous changes to time - either Administrator actuated or changed via an automated process. (Note that no continuous changes to time need to be logged. See also application note on FPT_STM_EXT.1) | For discontinuous changes to time: The old and new values for the time. Origin of the attempt to change time for success and failure (e.g., IP address). | <p>mgd 71079<br/>UI_CMDLINE_READ_LINE<br/>[junos@2636.1.1.1.2.164 username="root" command="set date 202005201815.00 "]<br/>User 'root', command 'set date 202005201815.00'</p> <p>mgd 71079<br/>UI_COMMIT_PROGRESS<br/>[junos@2636.1.1.1.2.164 message="signaling 'Network security daemon', pid 2641, signal 31, status 0 with notification errors enabled"] Commit operation in progress: signaling 'Network security daemon', pid 2641, signal 31, status 0 with notification errors enabled nsd 2641 NSD_SYS_TIME_CHANGE - System time has changed</p> <p>Below is the syslog message when time is updated by NTP:</p> <p>Oct 9 00:00:44 2025<br/>xntpd[16061]: ntpd 4.2.8p15-a Fri Feb 21 09:42:25 2025 (1): Starting</p> |

Table 3: Auditable Events (*Continued*)

| Requirement   | Auditable Events | Additional Audit Record Contents | How event generated                                                                                                                                                 |
|---------------|------------------|----------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|               |                  |                                  | Oct 9 00:00:44 2025<br>xntpd[16061]:<br>Command line: /usr/<br>sbin/xntpd -j -N -g<br>Sep 9 21:21:12 2025<br>xntpd[16061]: ntpd:<br>time reset<br>-2515178.383628 s |
| FPT_TST_EXT.1 | None             | None                             | Enter request system<br>fips self-test at<br>command line for on<br>demand self-test. or<br>Reboot the device to<br>view the self-test during<br>start-up.          |

**NOTE:** If there is a self-test error, you can recover the device via USB recovery.

If USB recovery fails, you can contact JTAC for support (<https://support.juniper.net/support/>).

**NOTE:** The status of a package installation or deletion is updated in the /var/log/ install file.

## RELATED DOCUMENTATION

Configuring Audit Log Options in the Evaluated Configuration | 61

# 7

CHAPTER

## Configuring Event Logging

---

### IN THIS CHAPTER

- Event Logging Overview | 97
  - Configuring Event Logging to a Local File | 98
  - Interpreting Event Messages | 98
  - Logging Changes to Secret Data | 100
  - Login and Logout Events Using SSH | 100
  - Logging of Audit Startup | 101
-

# Event Logging Overview

The evaluated configuration requires the auditing of configuration changes through the system log.

In addition, Junos OS can:

- Send automated responses to audit events (syslog entry creation).
- Allow authorized managers to examine audit logs.
- Send audit files to external servers.
- Allow authorized managers to return the system to a known state.

The logging for the evaluated configuration must capture the events. Some of the logging events are listed below:

- Changes to secret key data in the configuration.
- Committed changes.
- Login/logout of users.
- System startup.
- Failure to establish an SSH session.
- Establishment/termination of an SSH session.
- Changes to the (system) time.
- Termination of a remote session by the session locking mechanism.
- Termination of an interactive session.
- Changes to modification or deletion of cryptographic keys.
- Password resets.

In addition, Juniper Networks recommends that logging also:

- Capture all changes to the configuration.
- Store logging information remotely.

## RELATED DOCUMENTATION

[Interpreting Event Messages](#) | 98

# Configuring Event Logging to a Local File

You can configure storing of audit information to a local file with the `syslog` statement. This example stores logs in a file named **messages**:

```
[edit system]
syslog {
  file messages;
}
```

## RELATED DOCUMENTATION

[Event Logging Overview](#) | 97

# Interpreting Event Messages

The following output shows a sample event message.

```
Jul 24 17:43:28  router1 mgd[4163]: UI_CFG_AUDIT_SET_SECRET: User 'admin' set: [system radius-
server 1.2.3.4 secret]
```

[Table 4 on page 99](#) describes the fields for an event message. If the system logging utility cannot determine the value in a particular field, a hyphen ( - ) appears instead.

Table 4: Fields in Event Messages

| Field               | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           | Examples                                                                                                                                              |
|---------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------|
| <i>timestamp</i>    | <p>Time when the message was generated, in one of two representations:</p> <ul style="list-style-type: none"> <li><i>MMM-DD HH:MM:SS.MS+/-HH:MM</i>, is the month, day, hour, minute, second and millisecond in local time. The hour and minute that follows the plus sign (+) or minus sign (-) is the offset of the local time zone from Coordinated Universal Time (UTC).</li> <li><i>YYYY-MM-DDTHH:MM:SS.MSZ</i> is the year, month, day, hour, minute, second and millisecond in UTC.</li> </ul> | <p>Jul 24 17:43:28 is the timestamp expressed as local time in the United States.</p> <p>2012-07-24T09:17:15.719Z is 9:17 AM UTC on 24 July 2012.</p> |
| <i>hostname</i>     | Name of the host that originally generated the message.                                                                                                                                                                                                                                                                                                                                                                                                                                               | router1                                                                                                                                               |
| <i>process</i>      | Name of the Junos OS process that generated the message.                                                                                                                                                                                                                                                                                                                                                                                                                                              | mgd                                                                                                                                                   |
| <i>processID</i>    | UNIX process ID (PID) of the Junos OS process that generated the message.                                                                                                                                                                                                                                                                                                                                                                                                                             | 4153                                                                                                                                                  |
| <i>TAG</i>          | Junos OS system log message tag, which uniquely identifies the message.                                                                                                                                                                                                                                                                                                                                                                                                                               | UI_DBASE_LOGOUT_EVENT                                                                                                                                 |
| <i>username</i>     | Username of the user initiating the event.                                                                                                                                                                                                                                                                                                                                                                                                                                                            | "admin"                                                                                                                                               |
| <i>message-text</i> | English-language description of the event .                                                                                                                                                                                                                                                                                                                                                                                                                                                           | set: [system radius-server 1.2.3.4 secret]                                                                                                            |

## RELATED DOCUMENTATION

## Logging Changes to Secret Data

The following are examples of audit logs of events that change the secret data. Whenever there is a change in the configuration example, the syslog event should capture the below logs:

```
Jul 24 17:43:28 router1 mgd[4163]: UI_CFG_AUDIT_SET_SECRET: User 'admin' set: [system radius-server 1.2.3.4 secret]
Jul 24 17:43:28 router1 mgd[4163]: UI_CFG_AUDIT_SET_SECRET: User 'admin' set: [system login user admin authentication encrypted-password]
Jul 24 17:43:28 router1 mgd[4163]: UI_CFG_AUDIT_SET_SECRET: User 'admin' set: [system login user admin2 authentication encrypted-password]
```

Everytime a configuration is updated or changed, the syslog should capture these logs:

```
Jul 24 18:29:09 router1 mgd[4163]: UI_CFG_AUDIT_SET_SECRET: User 'admin' replace: [system radius-server 1.2.3.4 secret]
Jul 24 18:29:09 router1 mgd[4163]: UI_CFG_AUDIT_SET_SECRET: User 'admin' replace: [system login user admin authentication encrypted-password]
Jul 24 18:29:09 router1 mgd[4163]: UI_CFG_AUDIT_SET_SECRET: User 'admin' replace: [system login user admin authentication encrypted-password]
```

### RELATED DOCUMENTATION

[Interpreting Event Messages](#) | 98

## Login and Logout Events Using SSH

System log messages are generated whenever a user successfully or unsuccessfully attempts SSH access. Logout events are also recorded. For example, the following logs are the result of two failed authentication attempts, then a successful one, and finally a logout:

```
Dec 20 23:17:35 bilbo sshd[16645]: Failed password for op from 172.17.58.45 port 1673 ssh2
Dec 20 23:17:42 bilbo sshd[16645]: Failed password for op from 172.17.58.45 port 1673 ssh2
Dec 20 23:17:53 bilbo sshd[16645]: Accepted password for op from 172.17.58.45 port 1673 ssh2
```

```
Dec 20 23:17:53 bilbo mgd[16648]: UI_AUTH_EVENT: Authenticated user 'op' at permission level
                        'j-operator'
Dec 20 23:17:53 bilbo mgd[16648]: UI_LOGIN_EVENT: User 'op' login, class 'j-operator' [16648]
Dec 20 23:17:56 bilbo mgd[16648]: UI_CMDLINE_READ_LINE: User 'op', command 'quit '
Dec 20 23:17:56 bilbo mgd[16648]: UI_LOGOUT_EVENT: User 'op' logout
```

## RELATED DOCUMENTATION

[Interpreting Event Messages](#) | 98

# Logging of Audit Startup

The audit information logged includes startups of Junos OS. This in turn identifies the startup events of the audit system, which cannot be independently disabled or enabled. For example, if Junos OS is restarted, the audit log contains the following information:

```
Dec 20 23:17:35 bilbo syslogd: exiting on signal 14
Dec 20 23:17:35 bilbo syslogd: restart
Dec 20 23:17:35 bilbo syslogd /kernel: Dec 20 23:17:35 init: syslogd (PID 19128) exited with
status=1
Dec 20 23:17:42 bilbo /kernel:
Dec 20 23:17:53 init: syslogd (PID 19200) started
```

## RELATED DOCUMENTATION

[Login and Logout Events Using SSH](#) | 100

# 8

CHAPTER

## Configure MACsec

---

### IN THIS CHAPTER

- Overview of Media Access Control Security (MACsec) in FIPS mode | **103**
  - Configure MACsec | **105**
-

# Overview of Media Access Control Security (MACsec) in FIPS mode

Media Access Control Security (MACsec) is an 802.1AE IEEE industry-standard security technology that provides secure communication for all traffic on Ethernet links. MACsec provides point-to-point security on Ethernet links between directly connected nodes and is capable of identifying and preventing most security threats, including denial of service, intrusion, man-in-the-middle, masquerading, passive wiretapping, and playback attacks.

MACsec allows you to secure point to point Ethernet link for almost all traffic, including frames from the Link Layer Discovery Protocol (LLDP), Link Aggregation Control Protocol (LACP), Dynamic Host Configuration Protocol (DHCP), Address Resolution Protocol (ARP), and other protocols that are not typically secured on an Ethernet link because of limitations with other security solutions. MACsec can be used in combination with other security protocols such as IP Security (IPsec) and Secure Sockets Layer (SSL) to provide end-to-end network security.

MACsec is standardized in IEEE 802.1AE. The IEEE 802.1AE standard can be seen on the IEEE organization website at [IEEE 802.1: BRIDGING & MANAGEMENT](#).

Each implementation of an algorithm is checked by a series of known answer test (KAT) self-tests and crypto algorithms validations (CAV). The following cryptographic algorithms are added specifically for MACsec.

- Advanced Encryption Standard (AES)-Cipher Message Authentication Code (CMAC)
- Advanced Encryption Standard (AES) Key Wrap

Pre-shared key configurations for both connectivity association key name (CKN) and connectivity association key (CAK):

```
crypto-officer@hostname:fips# prompt security macsec connectivity-association connectivity-association-name pre-shared-key cak
New cak (secret):
Retype new cak (secret):
```

```
crypto-officer@hostname:fips# set security macsec connectivity-association ca_name pre-shared-key ckn ckn
```



**NOTE:** In the above set security macsec connectivity-association *ca\_name* pre-shared-key *ckn* *ckn* command, you need to define a user defined name for the *ca\_name* variable option and a user defined connectivity association key name in hexadecimal format for *ckn* variable option.

A pre-shared key is exchanged between directly-connected links to establish a MACsec-secure link. The pre-shared-key includes the CKN and the CAK. The CKN and CAK must match on both ends of a link to create a MACsec-secured link.

If you configure 128 bit cipher suite, then CAK can be 32 digit hexadecimal number. If you configure 256 bit cipher suite, then CAK can be 64 digit hexadecimal number.



**NOTE:** To maximize security, we recommend you to configure all 64 digits of a CKN and all 32 digits of a CAK. If you do not configure all 64 digits of a CKN or all 32 digits of a CAK, the system auto-configures all the remaining digits to 0. However, you will receive a warning message when you commit the configuration.

After the successful exchange and verification of the pre-shared keys by both ends of the link, the MACsec Key Agreement (MKA) protocol enables and manages the secure link. The MKA protocol then elects one of the two directly-connected devices as the key server. The key server then shares a random security with the other device over the MACsec-secure point-to-point link. The key server continues to periodically create and share a random security key with the other device over the MACsec-secured point-to-point link as long as MACsec is enabled.

For example, you can configure a CKN of 37c9c2c45ddd012aa5bc8ef284aa23ff6729ee2e4acb66e91fe34ba2cd9fe311 and CAK of 228ef255aa23ff6729ee664acb66e91f on connectivity association.

## RELATED DOCUMENTATION

[Understanding Media Access Control Security \(MACsec\)](#)

# Configure MACsec

## IN THIS SECTION

- [Customizing Time | 105](#)
- [Configuring MACsec on a Device Running Junos OS | 106](#)
- [Configuring Static MACsec with Layer 3 Traffic | 107](#)
- [Configuring MACsec with keychain using Layer 3 Traffic | 111](#)
- [Configuring Static MACsec for Layer 2 Traffic | 117](#)
- [Configuring MACsec with keychain for Layer 2 Traffic | 122](#)
- [Disable and Restart MACsec Sessions | 129](#)

We can configure MACsec to secure point-to-point Ethernet links connecting your device with MACsec-capable MICs. Each point-to-point Ethernet link that you want to secure using MACsec must be configured independently. We can enable MACsec on device-to-device links using static connectivity association key (CAK) security mode.

You can configure different interface rates such as 40G, 100G, and 10G in port mode and specific interface rates such as 100G, 40G, and 10G in pic mode. In pic mode you can configure only one type of interface speed.

## Customizing Time

To customize time, enable NTP or set the date from the Junos OS CLI.

### 1. Enable NTP.

```
[edit]
security-administrator@hostname:fips# set system ntp server 10.1.1..1 key 1
security-administrator@hostname:fips# set system ntp authentication-key 1 type [sha256] value
12345678
security-administrator@hostname:fips# set system ntp trusted-key 1
security-administrator@hostname:fips# commit
```

2. If you do not use NTP, set the date and time from the CLI. Date and time format is YYYYMMDDHHMM.ss

```
security-administrator@hostname:fips> set date 201803202034.00
security-administrator@hostname:fips> set cli timestamp
```

## Configuring MACsec on a Device Running Junos OS

To configure MACsec on a device running Junos OS:

1. Configure the MACsec security mode as for the connectivity association.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association
connectivity-association-name exclude-protocol protocol-name
security-administrator@hostname:fips# set security macsec connectivity-association
connectivity-association-name include-sci
security-administrator@hostname:fips# set security macsec connectivity-association
connectivity-association-name mka key-server-priority priority-number
security-administrator@hostname:fips# set security macsec connectivity-association
connectivity-association-name mka transmit-interval interval
security-administrator@hostname:fips# set security macsec connectivity-association
connectivity-association-name offset offset-number
```



**NOTE:** Based on your requirement you can configure the *offset-number* at the set security macsec connectivity-association *connectivity-association-name* offset hierarchy level to 0, 30, or 50.

2. Create the pre-shared key by configuring the connectivity association key name (CKN) and connectivity association key (CAK).

```
[edit]
security-administrator@hostname:fips# prompt security macsec connectivity-association
connectivity-association-name pre-shared-key cak
New cak (secret):
Retype new cak (secret):
security-administrator@hostname:fips# set security macsec connectivity-association
```

```
connectivity-association-name pre-shared-key ckn hexadecimal-number
security-administrator@hostname:fips# set security macsec connectivity-association
connectivity-association-name replay-protect replay-window-size number-of-packets
```



**NOTE:** Based on your requirement you can configure the *number-of-packets* value at the `set security macsec connectivity-association connectivity-association-name replay-protect replay-window-size` hierarchy level from 0 through 65535.

3. Set the MKA to security mode.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1
security-mode static-cak
```



**NOTE:** CA1 is an example of *connectivity-association-name* configured.

4. Assign the configured connectivity association with a specified MACsec interface.

```
[edit]
security-administrator@hostname:fips# set security macsec interfaces interface-name
connectivity-association connectivity-association-name
```

## Configuring Static MACsec with Layer 3 Traffic

To configure Static MACsec using ICMP traffic between device R0 and device R1:

In R0:

1. Create the preshared key by configuring the connectivity association key name (CKN) and connectivity association key (CAK)

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 pre-
shared-key ckn 234567892233445566778899222333444555666777888999222333344445555
security-administrator@hostname:fips# prompt security macsec connectivity-association CA1
pre-shared-key cak
```

```

New cak (secret):
Retype new cak (secret):
security-administrator@hostname:fips# set security macsec connectivity-association CA1
offset 30

```

2. Set the trace option values.

```

[edit]
security-administrator@hostname:fips# set security macsec traceoptions file MACsec.log
security-administrator@hostname:fips# set security macsec traceoptions file size 4000000000
security-administrator@hostname:fips# set security macsec traceoptions flag all

```

3. Assign the trace to an interface.

```

[edit]
security-administrator@hostname:fips# set security macsec interfaces interface-name
traceoptions file mka_xe size 1g
security-administrator@hostname:fips# set security macsec interfaces interface-name
traceoptions flag all

```

4. Configure the MACsec security mode as static-cak for the connectivity association.

```

[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1
security-mode static-cak

```

5. Set the MKA key server priority.

```

[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 mka
key-server-priority 1

```

6. Set the MKA transmit interval.

```

[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 mka
transmit-interval 3000

```

## 7. Enable the MKA secure.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1
include-sci
```

## 8. Assign the connectivity association to an interface.

```
[edit]
security-administrator@hostname:fips# set security macsec interfaces interface-name
connectivity-association CA1
security-administrator@hostname:fips# set interfaces interface-name unit 0 family inet
address 10.1.1.1/24
```

In R1:

## 1. Create the preshared key by configuring the connectivity association key name (CKN) and connectivity association key (CAK)

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 pre-
shared-key ckn 234567892233445566778899222333444555666777888999222333344445555
security-administrator@hostname:fips# prompt security macsec connectivity-association CA1
pre-shared-key cak
New cak (secret):
Retype new cak (secret):
security-administrator@hostname:fips# set security macsec connectivity-association CA1
offset 30
```

## 2. Set the trace option values.

```
[edit]
security-administrator@hostname:fips# set security macsec traceoptions file MACsec.log
security-administrator@hostname:fips# set security macsec traceoptions file size 4000000000
security-administrator@hostname:fips# set security macsec traceoptions flag all
```

3. Assign the trace to an interface.

```
[edit]
security-administrator@hostname:fips# set security macsec interfaces interface-name
traceoptions file mka_xe size 1g
security-administrator@hostname:fips# set security macsec interfaces interface-name
traceoptions flag all
```

4. Configure the MACsec security mode as static-cak for the connectivity association.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1
security-mode static-cak
```

5. Set the MKA transmit interval.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 mka
transmit-interval 3000
```

6. Enable the MKA secure.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1
include-sci
```

7. Assign the connectivity association to an interface.

```
[edit]
security-administrator@hostname:fips# set security macsec interfaces interface-name
connectivity-association CA1
security-administrator@hostname:fips# set interfaces interface-name unit 0 family inet
address 10.1.1.2/24
```

## Configuring MACsec with keychain using Layer 3 Traffic

Synchronize both macsec endpoint devices to NTP as both device's time should be the same for key start time triggers. To configure MACsec with keychain using ICMP traffic between device R0 and device R1:

In R0:

1. Assign a tolerance value to the authentication key chain.

```
[edit]
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 tolerance 20
```

2. Create the secret password to use. It is a string of hexadecimal digits up to 64 characters long. The password can include spaces if the character string is enclosed in quotation marks. The keychain's secret-data is used as a CAK.

You can configure upto 64 keys. For example, you can refer the following 4 keys:

```
[edit]
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 0 key-name 2345678922334455667788992223334445556667778889992222333344445551
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 0 start-time 2018-03-20.20:35
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 1 key-name 2345678922334455667788992223334445556667778889992222333344445552
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 1 start-time 2018-03-20.20:37
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 2 key-name 2345678922334455667788992223334445556667778889992222333344445553
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 2 start-time 2018-03-20.20:39
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 3 key-name 2345678922334455667788992223334445556667778889992222333344445554
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 3 start-time 2018-03-20.20:41
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 4 key-name 2345678922334455667788992223334445556667778889992222333344445555
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 4 start-time 2018-03-20.20:43
```

Use the prompt command to enter a secret key value. For example, the secret key value is *2345678922334455667788992223334123456789223344556677889922233341*.

You can configure upto 64 secret keys. For example, you can refer the following 4 secret keys:

```
[edit]
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 0 secret
New cak (secret):
Retype new cak (secret):
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 1 secret
New cak (secret):
Retype new cak (secret):
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 2 secret
New cak (secret):
Retype new cak (secret):
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 3 secret
New cak (secret):
Retype new cak (secret):
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 4 secret
New cak (secret):
Retype new cak (secret):
```

3. Associate the preshared keychain name with the connectivity association.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 pre-
shared-key-chain macsec-kc1
security-administrator@hostname:fips# set security macsec connectivity-association CA1
offset 50
security-administrator@hostname:fips# set security macsec connectivity-association CA1
cipher-suite gcm-aes-256
```



**NOTE:** The cipher value can also be set as **cipher-suite gcm-aes-128**.

4. Set the trace option values.

```
[edit]
security-administrator@hostname:fips# set security macsec traceoptions file MACsec.log
security-administrator@hostname:fips# set security macsec traceoptions file size 4000000000
security-administrator@hostname:fips# set security macsec traceoptions flag all
```

5. Assign the trace to an interface.

```
[edit]
security-administrator@hostname:fips# set security macsec interfaces interface-name
traceoptions file mka_xe size 1g
security-administrator@hostname:fips# set security macsec interfaces interface-name
traceoptions flag all
```

6. Configure the MACsec security mode as static-cak for the connectivity association.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1
security-mode static-cak
```

7. Set the MKA key server priority.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 mka
key-server-priority 1
```

8. Set the MKA transmit interval.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 mka
transmit-interval 3000
```

9. Enable the MKA secure.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1
include-sci
```

10. Assign the connectivity association to an interface.

```
[edit]
security-administrator@hostname:fips# set security macsec interfaces interface-name
connectivity-association CA1
security-administrator@hostname:fips# set interfaces interface-name unit 0 family inet
address 10.1.1.1/24
```

To configure MACsec with keychain for Layer 3 Traffic:

In R1:

1. Assign a tolerance value to the authentication key chain.

```
[edit]
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 tolerance 20
```

2. Create the secret password to use. It is a string of hexadecimal digits up to 64 characters long. The password can include spaces if the character string is enclosed in quotation marks. The keychain's secret-data is used as a CAK.

You can configure upto 64 keys. For example, you can refer the following 4 keys:

```
[edit]
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 0 key-name 2345678922334455667788992223334445556667778889992222333344445551
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 0 start-time 2018-03-20.20:35
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 1 key-name 2345678922334455667788992223334445556667778889992222333344445552
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 1 start-time 2018-03-20.20:37
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 2 key-name 2345678922334455667788992223334445556667778889992222333344445553
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 2 start-time 2018-03-20.20:39
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 3 key-name 2345678922334455667788992223334445556667778889992222333344445554
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 3 start-time 2018-03-20.20:41
```

```
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 4 key-name 234567892233445566778899222333444555666777888999222333344445555
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 4 start-time 2018-03-20.20:43
```

Use the prompt command to enter a secret key value. For example, the secret key value is *2345678922334455667788992223334123456789223344556677889922233341*.

You can configure upto 64 secret keys. For example, you can refer the following 4 secret keys:

```
[edit]
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 0 secret
New cak (secret):
Retype new cak (secret):
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 1 secret
New cak (secret):
Retype new cak (secret):
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 2 secret
New cak (secret):
Retype new cak (secret):
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 3 secret
New cak (secret):
Retype new cak (secret):
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 4 secret
New cak (secret):
Retype new cak (secret):
```

3. Associate the preshared keychain name with the connectivity association.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 pre-
shared-key-chain macsec-kc1
security-administrator@hostname:fips# set security macsec connectivity-association CA1
offset 50
security-administrator@hostname:fips# set security macsec connectivity-association CA1
cipher-suite gcm-aes-256
```

4.

**NOTE:**

- You can use the non-XPB ciphers AES-GCM-128 and AES-GCM-256 for 10G/xe interfaces macsec configuration only.
- You can use the XPB ciphers AES-GCM-XPB-128 and AES-GCM-XPB-256 for 40G and 100G rates macsec configuration. You can also use the XPB ciphers AES-GCM-XPB-128 and AES-GCM-XPB-256 for 10G/xe interfaces macsec configuration, if it supports.

5. Set the trace option values.

```
[edit]
security-administrator@hostname:fips# set security macsec traceoptions file MACsec.log
security-administrator@hostname:fips# set security macsec traceoptions file size 4000000000
security-administrator@hostname:fips# set security macsec traceoptions flag all
```

6. Assign the trace to an interface.

```
[edit]
security-administrator@hostname:fips# set security macsec interfaces interface-name
traceoptions file mka_xe size 1g
security-administrator@hostname:fips# set security macsec interfaces interface-name
traceoptions flag all
```

7. Configure the MACsec security mode as static-cak for the connectivity association.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1
security-mode static-cak
```

8. Set the MKA key server priority.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 mka
key-server-priority 1
```

9. Set the MKA transmit interval.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 mka
transmit-interval 3000
```

10. Enable the MKA secure.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1
include-sci
```

11. Assign the connectivity association to an interface.

```
[edit]
security-administrator@hostname:fips# set security macsec interfaces interface-name
connectivity-association CA1
security-administrator@hostname:fips# set interfaces interface-name unit 0 family inet
address 10.1.1.2/24
```

## Configuring Static MACsec for Layer 2 Traffic

To configure static MACsec for Layer 2 traffic between device R0 and device R1:

In R0:

1. Set the MKA key server priority.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 mka
key-server-priority 1
```

2. Create the secret password to use. It is a string of hexadecimal digits up to 64 characters long. The password can include spaces if the character string is enclosed in quotation marks. The keychain's secret-data is used as a CAK.

```
[edit]
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 0 secret
New cak (secret):
Retype new cak (secret):
```

For example, the secret key value is

*2345678922334455667788992223334123456789223344556677889922233341.*

3. Associate the preshared keychain name with the connectivity association.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 pre-
shared-key-chain macsec-kc1
security-administrator@hostname:fips# set security macsec connectivity-association CA1
offset 50
security-administrator@hostname:fips# set security macsec connectivity-association CA1
cipher-suite gcm-aes-256
```

4. Set the trace option values.

```
[edit]
security-administrator@hostname:fips# set security macsec traceoptions file MACsec.log
security-administrator@hostname:fips# set security macsec traceoptions file size 4000000000
security-administrator@hostname:fips# set security macsec traceoptions flag all
```

5. Assign the trace to an interface.

```
[edit]
security-administrator@hostname:fips# set security macsec interfaces interface-name
traceoptions file mka_xe size 1g
security-administrator@hostname:fips# set security macsec interfaces interface-name
traceoptions flag all
```

6. Configure the MACsec security mode as static-cak for the connectivity association.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1
security-mode static-cak
```

7. Set the MKA key server priority.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 mka
key-server-priority 1
```

8. Set the MKA transmit interval.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 mka
transmit-interval 3000
```

9. Enable the MKA secure.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1
include-sci
```

10. Assign the connectivity association to an interface.

```
[edit]
security-administrator@hostname:fips# set security macsec interfaces interface-name
connectivity-association CA1
```

11. Configure VLAN tagging.

```
[edit]
security-administrator@hostname:fips# set interfaces interface-name1 flexible-vlan-tagging
security-administrator@hostname:fips# set interfaces interface-name1 encapsulation flexible-
ethernet-services
security-administrator@hostname:fips# set interfaces interface-name1 unit 100 encapsulation
vlan-bridge
security-administrator@hostname:fips# set interfaces interface-name1 unit 100 vlan-id 100
```

```

security-administrator@hostname:fips# set interfaces interface-name2 flexible-vlan-tagging
security-administrator@hostname:fips# set interfaces interface-name2 encapsulation flexible-
ethernet-services
security-administrator@hostname:fips# set interfaces interface-name2 unit 100 encapsulation
vlan-bridge
security-administrator@hostname:fips# set interfaces interface-name2 unit 100 vlan-id 100

```

In R1:

1. Create the secret password to use. It is a string of hexadecimal digits up to 64 characters long. The password can include spaces if the character string is enclosed in quotation marks. The keychain's secret-data is used as a CAK.

```

[edit]
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 0 secret
New cak (secret):
Retype new cak (secret):

```

For example, the secret key value is

2345678922334455667788992223334123456789223344556677889922233341.

2. Associate the preshared keychain name with the connectivity association.

```

[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 pre-
shared-key-chain macsec-kc1
security-administrator@hostname:fips# set security macsec connectivity-association CA1
offset 50
security-administrator@hostname:fips# set security macsec connectivity-association CA1
cipher-suite gcm-aes-256

```

3. Set the trace option values.

```

[edit]
security-administrator@hostname:fips# set security macsec traceoptions file MACsec.log
security-administrator@hostname:fips# set security macsec traceoptions file size 4000000000
security-administrator@hostname:fips# set security macsec traceoptions flag all

```

4. Assign the trace to an interface.

```
[edit]
security-administrator@hostname:fips# set security macsec interfaces interface-name
traceoptions file mka_xe size 1g
security-administrator@hostname:fips# set security macsec interfaces interface-name
traceoptions flag all
```

5. Configure the MACsec security mode as static-cak for the connectivity association.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1
security-mode static-cak
```

6. Set the MKA key server priority.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 mka
key-server-priority 1
```

7. Set the MKA transmit interval.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 mka
transmit-interval 3000
```

8. Enable the MKA secure.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1
include-sci
```

9. Assign the connectivity association to an interface.

```
[edit]
security-administrator@hostname:fips# set security macsec interfaces interface-name
connectivity-association CA1
```

10. Configure VLAN tagging.

```
[edit]
security-administrator@hostname:fips# set interfaces interface-name1 flexible-vlan-tagging
security-administrator@hostname:fips# set interfaces interface-name1 encapsulation flexible-
ethernet-services
security-administrator@hostname:fips# set interfaces interface-name1 unit 100 encapsulation
vlan-bridge
security-administrator@hostname:fips# set interfaces interface-name1 unit 100 vlan-id 100
security-administrator@hostname:fips# set interfaces interface-name2 flexible-vlan-tagging
security-administrator@hostname:fips# set interfaces interface-name2 encapsulation flexible-
ethernet-services
security-administrator@hostname:fips# set interfaces interface-name2 unit 100 encapsulation
vlan-bridge
security-administrator@hostname:fips# set interfaces interface-name2 unit 100 vlan-id 100
```

## Configuring MACsec with keychain for Layer 2 Traffic

Synchronize both macsec endpoint devices to NTP as both device's time should be the same for key start time triggers. To configure MACsec with keychain for ICMP traffic between device R0 and device R1:

In R0:

1. Assign a tolerance value to the authentication key chain.

```
[edit]
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 tolerance 20
```

2. Create the secret password to use. It is a string of hexadecimal digits up to 64 characters long. The password can include spaces if the character string is enclosed in quotation marks. The keychain's secret-data is used as a CAK.

You can configure upto 64 keys. For example, you can refer the following 4 keys:

```
[edit]
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 0 key-name 2345678922334455667788992223334445556667778889992222333344445551
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 0 start-time 2018-03-20.20:35
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 1 key-name 2345678922334455667788992223334445556667778889992222333344445552
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 1 start-time 2018-03-20.20:37
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 2 key-name 2345678922334455667788992223334445556667778889992222333344445553
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 2 start-time 2018-03-20.20:39
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 3 key-name 2345678922334455667788992223334445556667778889992222333344445554
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 3 start-time 2018-03-20.20:41
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 4 key-name 2345678922334455667788992223334445556667778889992222333344445555
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 4 start-time 2018-03-20.20:43
```

Use the prompt command to enter a secret key value. For example, the secret key value is 2345678922334455667788992223334123456789223344556677889922233341.

You can configure upto 64 secret keys. For example, you can refer the following 4 secret keys:

```
[edit]
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 0 secret
New cak (secret):
Retype new cak (secret):
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 1 secret
New cak (secret):
Retype new cak (secret):
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 2 secret
New cak (secret):
Retype new cak (secret):
```

```

security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 3 secret
New cak (secret):
Retype new cak (secret):
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 4 secret
New cak (secret):
Retype new cak (secret):

```

3. Associate the preshared keychain name with the connectivity association.

```

[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 pre-
shared-key-chain macsec-kc1
security-administrator@hostname:fips# set security macsec connectivity-association CA1
cipher-suite gcm-aes-256

```

4. Set the trace option values.

```

[edit]
security-administrator@hostname:fips# set security macsec traceoptions file MACsec.log
security-administrator@hostname:fips# set security macsec traceoptions file size 4000000000
security-administrator@hostname:fips# set security macsec traceoptions flag all

```

5. Assign the trace to an interface.

```

[edit]
security-administrator@hostname:fips# set security macsec interfaces interface-name
traceoptions file mka_xe size 1g
security-administrator@hostname:fips# set security macsec interfaces interface-name
traceoptions flag all

```

6. Configure the MACsec security mode as static-cak for the connectivity association.

```

[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1
security-mode static-cak

```

7. Set the MKA key server priority.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 mka
key-server-priority 1
```

8. Set the MKA transmit interval.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 mka
transmit-interval 3000
```

9. Enable the MKA secure.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1
include-sci
```

10. Assign the connectivity association to an interface.

```
[edit]
security-administrator@hostname:fips# set security macsec interfaces interface-name
connectivity-association CA1
```

11. Configure VLAN tagging.

```
[edit]
security-administrator@hostname:fips# set interfaces interface-name1 flexible-vlan-tagging
security-administrator@hostname:fips# set interfaces interface-name1 encapsulation flexible-
ethernet-services
security-administrator@hostname:fips# set interfaces interface-name1 unit 100 encapsulation
vlan-bridge
security-administrator@hostname:fips# set interfaces interface-name1 unit 100 vlan-id 100
security-administrator@hostname:fips# set interfaces interface-name2 flexible-vlan-tagging
security-administrator@hostname:fips# set interfaces interface-name2 encapsulation flexible-
ethernet-services
security-administrator@hostname:fips# set interfaces interface-name2 unit 100 encapsulation
vlan-bridge
security-administrator@hostname:fips# set interfaces interface-name2 unit 100 vlan-id 100
```

In R1:

1. Assign a tolerance value to the authentication key chain.

```
[edit]
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 tolerance 20
```

2. Create the secret password to use. It is a string of hexadecimal digits up to 64 characters long. The password can include spaces if the character string is enclosed in quotation marks. The keychain's secret-data is used as a CAK.

You can configure upto 64 keys. For example, you can refer the following 4 keys:

```
[edit]
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 0 key-name 2345678922334455667788992223334445556667778889992222333344445551
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 0 start-time 2018-03-20.20:35
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 1 key-name 2345678922334455667788992223334445556667778889992222333344445552
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 1 start-time 2018-03-20.20:37
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 2 key-name 2345678922334455667788992223334445556667778889992222333344445553
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 2 start-time 2018-03-20.20:39
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 3 key-name 2345678922334455667788992223334445556667778889992222333344445554
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 3 start-time 2018-03-20.20:41
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 4 key-name 2345678922334455667788992223334445556667778889992222333344445555
security-administrator@hostname:fips# set security authentication-key-chains key-chain
macsec-kc1 key 4 start-time 2018-03-20.20:43
```

Use the prompt command to enter a secret key value. For example, the secret key value is 2345678922334455667788992223334123456789223344556677889922233341.

You can configure upto 64 secret keys. For example, you can refer the following 4 secret keys:

```
[edit]
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 0 secret
New cak (secret):
Retype new cak (secret):
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 1 secret
New cak (secret):
Retype new cak (secret):
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 2 secret
New cak (secret):
Retype new cak (secret):
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 3 secret
New cak (secret):
Retype new cak (secret):
security-administrator@hostname:fips# prompt security authentication-key-chains key-chain
macsec-kc1 key 4 secret
New cak (secret):
Retype new cak (secret):
```

3. Associate the preshared keychain name with the connectivity association.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 pre-
shared-key-chain macsec-kc1
security-administrator@hostname:fips# set security macsec connectivity-association CA1
cipher-suite gcm-aes-256
```

4. Set the trace option values.

```
[edit]
security-administrator@hostname:fips# set security macsec traceoptions file MACsec.log
security-administrator@hostname:fips# set security macsec traceoptions file size 4000000000
security-administrator@hostname:fips# set security macsec traceoptions flag all
```

5. Assign the trace to an interface.

```
[edit]
security-administrator@hostname:fips# set security macsec interfaces interface-name
traceoptions file mka_xe size 1g
security-administrator@hostname:fips# set security macsec interfaces interface-name
traceoptions flag all
```

6. Configure the MACsec security mode as static-cak for the connectivity association.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1
security-mode static-cak
```

7. Set the MKA key server priority.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 mka
key-server-priority 1
```

8. Set the MKA transmit interval.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1 mka
transmit-interval 3000
```

9. Enable the MKA secure.

```
[edit]
security-administrator@hostname:fips# set security macsec connectivity-association CA1
include-sci
```

## 10. Assign the connectivity association to an interface.

```
[edit]
security-administrator@hostname:fips# set security macsec interfaces interface-name
connectivity-association CA1
```

## 11. Configure VLAN tagging.

```
[edit]
security-administrator@hostname:fips# set interfaces interface-name1 flexible-vlan-tagging
security-administrator@hostname:fips# set interfaces interface-name1 encapsulation flexible-
ethernet-services
security-administrator@hostname:fips# set interfaces interface-name1 unit 100 encapsulation
vlan-bridge
security-administrator@hostname:fips# set interfaces interface-name1 unit 100 vlan-id 100
security-administrator@hostname:fips# set interfaces interface-name2 flexible-vlan-tagging
security-administrator@hostname:fips# set interfaces interface-name2 encapsulation flexible-
ethernet-services
security-administrator@hostname:fips# set interfaces interface-name2 unit 100 encapsulation
vlan-bridge
security-administrator@hostname:fips# set interfaces interface-name2 unit 100 vlan-id 100
```

## Disable and Restart MACsec Sessions

To disable and restart the MACsec sessions use the following configurations:

- To disable the MACsec session:

```
user@host# deactivate security macsec
```

- To restart the MACsec session:

```
user@host# run restart dot1x-protocol
```

or

```
user@host# activate security macsec
```

# 9

CHAPTER

## Performing Self-Tests on a Device

---

### IN THIS CHAPTER

- [Understanding FIPS Self-Tests | 132](#)
-

# Understanding FIPS Self-Tests

## IN THIS SECTION

- [Performing Power-On Self-Tests on the Device | 133](#)

The cryptographic module enforces security rules to ensure that a device running the Juniper Networks Junos operating system (Junos OS) in FIPS mode of operation meets the security requirements of FIPS 140-3 Level 1. To validate the output of cryptographic algorithms approved for FIPS and test the integrity of some system modules, the device performs the following series of known answer test (KAT) self-tests:

- `kernel`—KAT for kernel cryptographic routines
- `MACSec`—KAT for MACsec cryptographic implementation
- `libmd`—KAT for libmd
- `OpenSSL`—KAT for OpenSSL cryptographic implementation

The KAT self-tests are performed automatically at startup and reboot when FIPS mode of operation is enabled on the device. Conditional self-tests are also performed automatically to verify digitally signed software packages, generated random numbers, RSA and DSA key pairs, and manually entered keys.

On demand, self tests can be executed by entering `request system fips self-test` at command line.

If the KATs are completed successfully, the system log (`syslog`) file is updated to display the tests that were executed.

If the device fails a KAT, the device writes the details to a system log file, enters FIPS error state (panic), and reboots.

The system performs power-on tests, software integrity tests, noise source health tests (used for generating entropy), and Known Answer Tests. If power-on tests or noise source health tests fail, the device resets. If software integrity tests fail, the device automatically resets and restores the system from a recovery snapshot.

During software loading, the module displays the following output:

```
Initializing Verified Exec:
FIPS veriexec ECDSA Verify Known Answer Test: Passed
```

```
Verified os-kernel-prd-arm-64-20260112 signed by PackageProductionECP256_2026 method
ECDSA256+SHA256
Enforcing Verified Exec:
```

The file `show /var/log/messages` command displays the system log. See FPT\_TST\_EXT.1 under [Table 3 on page 65](#).

## Performing Power-On Self-Tests on the Device

Each time the cryptographic module is powered on, the module tests that the cryptographic algorithms still operate correctly and that sensitive data has not been damaged.

The module displays the following status output while running the power-on self-tests:

```
@ 1556787428 mgd start
Creating initial configuration: ...
mgd: Running FIPS Self-tests
random: HMAC-DRBG with SHA2-512 chosen
sysctl_warn_reuse: can't re-use a leaf (kern.random.hmac-drbg.hash)!
mgd: Testing kernel KATS:
mgd: NIST 800-90 HMAC DRBG Known Answer Test:          Passed
mgd: HMAC-SHA1 Known Answer Test:                      Passed
mgd: HMAC-SHA2-256 Known Answer Test:                  Passed
mgd: SHA-2-384 Known Answer Test:                      Passed
mgd: SHA-2-512 Known Answer Test:                      Passed
mgd: AES128-CMAC Known Answer Test:                    Passed
mgd: AES-CBC Known Answer Test:                        Passed
mgd: Testing MACSec KATS:
mgd: AES128-CMAC Known Answer Test:                    Passed
mgd: AES256-CMAC Known Answer Test:                    Passed
mgd: AES-ECB Known Answer Test:                        Passed
mgd: AES-KEYWRAP Known Answer Test:                    Passed
mgd: KBKDF Known Answer Test:                          Passed
mgd: Testing libmd KATS:
mgd: HMAC-SHA1 Known Answer Test:                      Passed
mgd: HMAC-SHA2-256 Known Answer Test:                  Passed
mgd: SHA-2-512 Known Answer Test:                      Passed
mgd: Testing OpenSSL KATS:
mgd: FIPS ECDSA Known Answer Test:                    Passed
mgd: FIPS ECDH Known Answer Test:                     Passed
mgd: HMAC-SHA1 Known Answer Test:                      Passed
mgd: HMAC-SHA2-224 Known Answer Test:                  Passed
```

|                                                    |        |
|----------------------------------------------------|--------|
| mgd: HMAC-SHA2-256 Known Answer Test:              | Passed |
| mgd: HMAC-SHA2-384 Known Answer Test:              | Passed |
| mgd: HMAC-SHA2-512 Known Answer Test:              | Passed |
| mgd: AES-CBC Known Answer Test:                    | Passed |
| mgd: AES-GCM Known Answer Test:                    | Passed |
| mgd: RSA-ENC Known Answer Test:                    | Passed |
| mgd: RSA-SIGN Known Answer Test:                   | Passed |
| mgd: KDF-IKE-V1 Known Answer Test:                 | Passed |
| mgd: KDF-SSH-SHA256 Known Answer Test:             | Passed |
| mgd: KDF-TLS12-PRF Known Answer Test:              | Passed |
| mgd: KDF-TLS13-KDF-EXTRACT Known Answer Test:      | Passed |
| mgd: KDF-TLS13-KDF-EXPAND Known Answer Test:       | Passed |
| mgd: KDF-X942 Known Answer Test:                   | Passed |
| mgd: KDF-X963 Known Answer Test:                   | Passed |
| mgd: KAS-ECC-EPHEM-UNIFIED-NOKC Known Answer Test: | Passed |
| mgd: KAS-FFC-EPHEM-NOKC Known Answer Test:         | Passed |
| mgd: Testing QuickSec 7.0 KATS:                    |        |
| mgd: HMAC-SHA1 Known Answer Test:                  | Passed |
| mgd: HMAC-SHA2-224 Known Answer Test:              | Passed |
| mgd: HMAC-SHA2-256 Known Answer Test:              | Passed |
| mgd: HMAC-SHA2-384 Known Answer Test:              | Passed |
| mgd: HMAC-SHA2-512 Known Answer Test:              | Passed |
| mgd: AES-CBC Known Answer Test:                    | Passed |
| mgd: AES-GCM Known Answer Test:                    | Passed |
| mgd: SSH-RSA-ENC Known Answer Test:                | Passed |
| mgd: SSH-RSA-SIGN Known Answer Test:               | Passed |
| mgd: SSH-ECDSA-SIGN Known Answer Test:             | Passed |
| mgd: KDF-IKE-V1 Known Answer Test:                 | Passed |
| mgd: KDF-IKE-V2 Known Answer Test:                 | Passed |
| mgd: Testing QuickSec KATS:                        |        |
| mgd: HMAC-SHA1 Known Answer Test:                  | Passed |
| mgd: HMAC-SHA2-224 Known Answer Test:              | Passed |
| mgd: HMAC-SHA2-256 Known Answer Test:              | Passed |
| mgd: HMAC-SHA2-384 Known Answer Test:              | Passed |
| mgd: HMAC-SHA2-512 Known Answer Test:              | Passed |
| mgd: AES-CBC Known Answer Test:                    | Passed |
| mgd: AES-GCM Known Answer Test:                    | Passed |
| mgd: SSH-RSA-ENC Known Answer Test:                | Passed |
| mgd: SSH-RSA-SIGN Known Answer Test:               | Passed |
| mgd: KDF-IKE-V1 Known Answer Test:                 | Passed |
| mgd: KDF-IKE-V2 Known Answer Test:                 | Passed |
| mgd: Testing SSH IPsec KATS:                       |        |
| mgd: HMAC-SHA1 Known Answer Test:                  | Passed |

```
mgd: HMAC-SHA2-256 Known Answer Test:      Passed
mgd: AES-CBC Known Answer Test:             Passed
mgd: SSH-RSA-ENC Known Answer Test:         Passed
mgd: SSH-RSA-SIGN Known Answer Test:        Passed
mgd: KDF-IKE-V1 Known Answer Test:         Passed
mgd: Testing file integrity:
mgd: File integrity Known Answer Test:      Passed
mgd: Testing crypto integrity:
mgd: Crypto integrity Known Answer Test:    Passed
mgd: Expect an exec Authentication error...
mgd: /sbin/kats/run-tests: /sbin/kats/cannot-exec: Authentication error
mgd: FIPS Self-tests Passed
```



**NOTE:** The module implements cryptographic libraries and algorithms that are not utilized in the approved mode of operation.

# 10

CHAPTER

## Operational Commands

---

### IN THIS CHAPTER

- [request system zeroize](#) | 137
-

# request system zeroize

## IN THIS SECTION

- [Syntax | 137](#)
- [Description | 137](#)
- [Options | 137](#)
- [Required Privilege Level | 137](#)
- [Output Fields | 137](#)
- [Sample Output | 138](#)
- [Release Information | 138](#)

---

## Syntax

**request system zeroize**

## Description

Erase and replace with zeros all user-created data from Routing Engines.

## Options

none—Zeroize all Routing Engines in Junos OS in FIPS mode. You must verify the request by typing **yes** to proceed. This command is restricted to Crypto Officers because the `maintenance` permission bit is one of the permission bits, along with `secret` and `control`, that distinguishes Crypto Officers from other FIPS users.

## Required Privilege Level

`maintenance`

## Output Fields

When you enter this command, you are provided feedback on the status of your request.

## Sample Output

### **request system zeroize**

```
crypto-officer@switch:fips> request system zeroize
warning: System will be rebooted and may not boot without configuration
Erase all data, including configuration and log files?. In case of Dual RE system, both Routing
Engines will be zeroized [yes,no] (no) yes

warning: ipsec-key-management subsystem not running - not needed by configuration.
warning: zeroizing localre
```

## Release Information

Command introduced in Junos OS Release 12.1.